card?

+G

A Centronics Parallel Printer Interface With Graphics For The VIC-20™ and C-64™ Computers

CARD/PRINT +G - INSTRUCTION MANUAL

CARDCO, Inc.   -   (316) 267-6525

GUARANTEE

For as long as this product is owned by its
original owner, CARDCO, Inc. will repair or
replace any defective parts or the entire
unit if it should become inoperative due to a
defect in manufacture or materials, providing
the unit is returned to CARDCO, Inc. in
undamaged condition with proof of purchase
(purchase receipt).

This product was developed by:

CARDCO, Inc.
300 S. Topeka
Wichita, Ks.
   67202

CARD/PRINT +G - INSTRUCTION MANUAL

CARDCO, Inc. - (316) 267-6525

TABLE OF CONTENTS

APPENDIX

SAMPLE PROGRAMS

FIRST Printing – FIRST Revision

CARD/PRINT +G - INSTRUCTION MANUAL

CARDCO, Inc.   -   (316) 267-6525

SPECIAL NOTE TO ALL
****

Within the text of this manual references
are made to many printers and printer types.
The C/?+G interface was intended to be used
only with printers that conform to certain
standards. There are four groups of printers
that are intended to be used with the C/?+G
interface. Within each group there may be
many printers. The four groups are the Epson
group, the Prowriter group, the Okidata group
and the Siekosha group. A listing of the
most common printers in each group is on page
A1 of the appendix of this manual. When, in
this manual, we refer to one of the printers
in a group the statement will refer to all
printers in that group.

If your printer isn't listed in one of
those groups it may still be in one of them,
we just aren't aware of it. If this is the
case and you find that your printer works
when set up like one of the printers in one
of the groups, please let us know so we can
pass on the information to other users.

Any printer can be used with the C/?+G
(See page A1 of the appendix for OTHER
PRINTERS) but the special Commodore functions
and Commodore graphics will not be
available.

CARD/PRINT +G - INSTRUCTION MANUAL

CARDCO, Inc. - (316) 267-6525

INTRODUCTION

The "CARD/?+G" (CARD/PRINT) printer interface was designed to allow you to add most parallel printers to your VIC-2Ø or C-64 computer. The design objective was to provide you with a system that would so closely duplicate the functions of the VIC printers that you would be able to run available software without any changes. To accomplish this task, and still allow you to make use of the special features available in today's high quality printers, required some special approaches to solving simple problems.

If you plan to write your own programs or customize existing software to enable the use of special features of your printer this manual should become your companion and best friend.

We have tried in this manual to document and fully explain each and every feature and function of our interface and how it will affect the operation of your system. We have provided examples and sample programs in an attempt to make each function understandable and useful to even a novice programmer.

HOOK UP PROCEDURES

1.   SEE APPENDIX PAGE A1 FOR INSTRUCTIONS
      ON SETTING THE INTERFACE DIP SWITCHES.

2.   TURN OFF YOUR COMPUTER AND PRINTER.
      INSERT THE SIX PIN PLUG ON THE END
      OF THE THICK ROUND CABLE INTO THE
      MATCHING PORT ON YOUR COMPUTER. (IF
      YOU ARE USING A DISK DRIVE THEN YOU
      WILL HAVE TO PLUG THE SIX PIN PLUG
      INTO THE BACK OF YOUR DISK DRIVE.)

3.   INSERT THE BIG BLUE PLUG ON THE END OF
      THE FLAT RIBBON CABLE INTO THE PORT ON
      YOUR PRINTER.

4.   PLUG THE CONNECTOR ON THE END OF THE
      THIN WIRE INTO THE CASSETTE PORT ON
      THE COMPUTER BEING SURE THAT THE
      CONNECTOR FACES DOWN, AND THE SMALL
      CIRCUIT BOARD IS ABOVE THE CONNECTOR.
      NOW, PLUG THE CASSETTE (IF YOU ARE
      USING ONE)ONTO SMALL CIRCUIT BOARD AND
      IT WILL OPERATE NORMALLY.

5.   TURN ON THE PRINTER AND THE COMPUTER
      IN THAT ORDER. (ALWAYS TURN ON THE
      PRINTER FIRST WHEN USING THE "C/?+G").

6. NOW: YOU TYPE: OPEN 4,4 <RETURN>
COMPUTER SAYS: "READY"
YOU TYPE: CMD4 <RETURN>

7. ONE OF TWO THINGS WILL HAPPEN:

**A. YOUR PRINTER RESPONDS BY PRINTING 'READY'. IF SO, YOU HAVE FINISHED THE HOOK UP AND YOU ARE READY TO GO ON TO THE NEXT SECTION.

**B. IF YOUR SCREEN DISPLAYS "DEVICE NOT PRESENT ERROR" OR THE PRINTER DOES NOT PRINT 'READY' SOMETHING IS WRONG. TURN YOUR PRINTER AND COMPUTER OFF AND REPEAT THE HOOK UP AGAIN, CAREFULLY. (PLEASE BE SURE ALL THREE CABLES ARE CONNECTED.)

IF ALL FAILS CONTACT YOUR DEALER, OR CALL US AT (316) 267-6525 BETWEEN 9 AM & 5 PM. CST MONDAY THRU FRIDAY.

REMEMBER THIS: WE WANT YOU TO BE TOTALLY SATISFIED WITH OUR PRODUCTS, AND WE WILL SPEND THE TIME NECESSARY TO HELP YOU GET YOUR SYSTEM RUNNING. OUR CUSTOMERS ARE OUR BEST ASSET

CARD/PRINT +G - INSTRUCTION MANUAL

CARDCO, Inc. - (316) 267-6525

RUNNING EXISTING PROGRAMS

Your interface was designed to allow you to run most standard programs available for the VIC-20 and COMMODORE-64 without any changes. For example, the "EASY SCRIPT" word processor package runs totally as it was designed to with the "CARD/?+G" interface and a "SILVER REED" Daisy Wheel printer. So will most other programs on most other printers. A few programs might require some small changes, but after reading this manual you should be able to handle them. If you run into a severe problem, write or call us. We want to get you on line!!!

WRITING YOUR OWN PROGRAMS

The rest of this manual is going to be devoted to explaining how to write and/or edit your own programs. We will split this into three parts. In the first part, we will tell you about your computer's command format. In the second we will deal with the "CARD/?+G"'s commands. And in the third part, we will relate all of this to your printer's abilities.

To make the most of this educational manual, we strongly suggest that you try the examples and see how they react on your printer. Some printers have features that others don't, but all the features of any printer can be accessed from a VIC-20 or a C-64 using the "CARD/?+G" interface.

BUT HOW DO I MAKE IT PRINT?

If you have made it this far, you deserve a pat on the back for picking a system that works and getting it up and running. Now comes the fun part. Type in and run this sample program:

```
10    X = 32:OPEN4,4,4
20    PRINT#4,CHR$(X);:X = X+1
30    IF X = 128 THEN X = 160
40    IF X <> 256 THEN20
```

You have just printed the standard character set that comes with your printer. You may have noted that we did not use any characters less than 32 or between 128 and 160, this is because they are reserved for special printer functions. (See the appendix page # A3) For example try this:

```
OPEN4,4:PRINT#4,CHR$(12):CLOSE4 <RETURN>
```

If you just lost a sheet of paper then your printer honors chr$(12) as an automatic form feed to get to the top of the next page without you having to figure out where it is. This form of telling the printer what to do is accomplished by simply 'printing' a command code chr$. These codes are contained in the instructions that came with your printer. I would suggest at this time that you get to know them because these codes are the keys that will allow you to unlock all the special features of your printer.

CARD/PRINT +G - INSTRUCTION MANUAL

CARDCO, Inc.   -   (316) 267-6525

COMMODORE COMMAND FORMAT
???????????????????????????

Commodore designed some really outstanding features into your computer but made a few normally easy things hard to do in the process. Getting the printer to print on paper what you print on the screen is not as easy as it should be, but with a little patience it can be mastered.

Your computer calls everything connected to it a device, and each device has a number so the computer can know what type of accessory it is talking to. It sends information to different types of devices in different codes.

PRINTERS HAVE DEVICE NUMBERS OF 4, 5, 6 & 7

To talk to a printer, you must open a channel. This can be done either in the direct mode as a statement, or it can be done within a program as a program line. But it must be done or you will not be able to communicate with the printer.

One thing you must be careful of is that a channel can be opened only once. You can use it all you want while it is open; but if you try to open an already opened channel you will get a FILE OPEN ERROR. So it is good practice to close each channel as soon as you are done with it.

The format for opening a channel is:

OPEN(file number),(device number),(command)

The format for closing a channel is:

CLOSE(file number)

The "FILE NUMBER" can be any number that you choose to call that file. This number must be between 1 & 255. This is the number you will use whenever you want to communicate with your printer. This is also the number you must use to close the FILE (close the channel of communication). Additionally, any file number of 128 or greater will cause the printer to add a line feed <chr$(1Ø)> after each carriage return <chr$(13)> causing some printers to double space and not permitting the use of some special printer functions that may be available with your printer.

The "DEVICE NUMBER" is simply the number of your printer as determined by the "CARD/?+G" interface. It is set at the factory to device 4, as this is the accepted standard. The device number can be changed to device 5 if desired so as to allow the use of two printers at the same time. (Refer to the appendix which deals with the DIP switch settings for your CARD/?+G interface).

The "SECONDARY ADDRESS" or command number is the third and last number in the command. It may be omitted, and in that case, a secondary address of Ø will be inserted automatically by the computer. The secondary address is used by the computer to send information to the printer; or in the case of our product, to the microprocessor in the interface box.   A complete listing of these commands and examples of how to use them starts on page # 13.

So, the command to open communications with your printer is:

The word OPEN followed by:

The FILE NUMBER (Ø to 255) and a comma
The DEVICE NUMBER (4 or 5) and a comma
An optional SECONDARY ADDRESS (Ø to 28)

And the command to end the conversation would be:

The word CLOSE followed by:

The FILE NUMBER (the same one used in open statement)

COMMODORE SPECIAL PRINTER CODES
****

Commodore printers use some special codes to accomplish tabbing, graphics and other functions that are unique to Commodore. To allow total compatibility with pre-existing Commodore programs we have implemented these functions in the C/?+G interface. These functions should be considered as a bonus you got when you bought the C/?+G, because they will give you another way to accomplish some special printing chores.

Most of these commands are probably available in your printer, but in some cases the Commodore printer versions may be easier to use. In other cases, however, the Commodore versions may interefere with what you want to do. So we only implemented these commands in the normal printing modes (secondary addresses Ø,1,7 & 8) to allow you to turn them off if desired.

A detailed list of these commands can be found in the appendix of this manual. Be sure to read this section if you want to get the most out of your system.

NOW THAT YOU CAN TALK TO THE PRINTER
****

Now that we have an open file that we can
use to tell the printer what to do, you have
to make a choice between two formats to use
to get the printer to listen to you.

CHOICE # 1:
                        CMD#
                        ****

This format is generally the easiest to
use to get the printer to print something.
In this mode, everything that would normally
be sent to the screen is sent to the printer.
This is usually a very easy mode to use
because by now you are probably quite use to
printing things to the screen and most of the
same rules apply to printing things to the
printer.

Let's try a simple sample. Enter and RUN:

```
10   OPEN4,4:A$=""
20   PRINT#4,A$;"THIS IS A TEST"
30   A$=" <16 spaces>   "+A$:A=A+1
40   IF A<4 THEN 20
50   PRINT#4:CLOSE4:END
```

I told you it was a simple sample, but it should give you an example of how to set up a program to print to the screen using the CMD statement.

Remember that in order to get back to printing to the screen you must redirect the information by closing the file, or opening a channel to the screen. Adding to the program to allow printing to the screen would result in the following:

```
10 OPEN4,4:CMD4
20 PRINT"TEST":I=I+1:IFI=5THEN40
30 GOTO 20
40 OPEN3,3:CMD3:CLOSE4:PRINT"<CLR>DONE":
   CLOSE3:END
```

OR LINE 40 COULD READ

```
40 PRINT#4 : CLOSE4:PRINT"<CH>DONE":END
```

NOTE: <CLR> MEANS SHIFTED CLEAR/HOME KEY

As we stated earlier most of the print statements that you use to print to the screen also will print to the printer. However, there are some statements that just won't work no matter how hard you try. These statements are covered in the addendum of this book starting at page # A5.

CHOICE # 2:
PRINT#
******

    Printing using the "PRINT#" statement is similar to the CMD format except that you must use the "PRINT#" statement before every item you want to print. The "PRINT#" statement must be followed by the file number of an open file and a comma.

              PRINT#(file number),

Again, let's try a sample program:

```
10   PRINT"<CH>":OPEN4,4
20   PRINT#4,A
30   PRINTA:A=A+1:IFA=5THEN50
40   GOTO20
50   CLOSE4:END
```

    Notice that using this format it is easier to print to both the screen and the printer. The disk drive can also be easily accessed using this format. But be sure to keep track of what files you have open and where you are sending the information.

    As before, remember it is a good idea to close each file as soon as you are done using it. The "PRINT#" function has some strange properties just like the "CMD" function and these are covered in the same section as above starting on page # A5.

C/?+G OPEN COMMANDS
****

This refers to the secondary command as used
in each open statement (see page 11).

SECONDARY
ADDRESS   FUNCTION

0 (or null)   normal printing mode
               (upper case/graphics mode)
               also called the **CURSOR UP** mode
               upper case only with line feed
               (see pages 18-21)

1   normal printing mode
               (upper case/graphics mode)
               also called the **CURSOR UP** mode
               upper case only no line feed
               (see pages 18-21 & 15-16)

2   reserved

3   hexidecimal mode
               all characters sent from your
               computer to the printer will
               be printed out in their hexi
               decimal equivalent.
               (see page 30)

4	transparent mode with line feed (see page 27)
5	transparent mode no line feed (see page 27 & 15-16)
6	character mode this will print all characters from the C/?+G internal ROM. (see page 31)
7	normal printing mode (upper/lower case mode) also called **CURSOR DOWN** mode upper/lower case with line feed (see pages 18-22)
8	normal printing mode (upper/lower case mode) also called **CURSOR DOWN** mode upper/lower case no line feed (see pages 18-22 & 15-16)
20+ any of the above	lock mode, locks in the command given. (ie. OPEN x,4,25 locks in the transparent mode without line feed.) (see page 29)

AUTO LINE FEED
****

Automatic   line   feed   is   an   option
available in most print   modes   and   we   will
cover   it   only once because it will apply to
all modes in the same way.

Most printers come from the   factory   set
to   print   each line of characters when given
the command from the computer to do so.   This
command   is CHR$(13).   After this command the
printer returns to the start of the same line
to   print   more data.   It will not advance to
the start of the next line (line feed) unless
told   to   do so.   To find out if your printer
falls into this category, please consult your
printer's instruction manual.

There   is   usually a method provided with
most printers to add   the   necessary   command
data to automatically go on to the next line,
but this   method   may   require   disassembling
your printer, or at least turning the printer
off and switching a switch.   Aside from being
time   consuming this method usually cannot be
accomplished from within a program.

There are many benefits of being able   to
return   the   printer   to the beginning of the
same   line,   but   printing   the   command   to
advance   the paper (CHR$(10)) after each line
can be time and memory consuming.   Also   the
VIC   printers   from   Commodore   do   line feed

automatically, so to use programs written for these printers an auto line feed function is necessary.

Fear not brave computerist, CARDCO, Inc., to the rescue. Within the command format of the "CARD/?+G" interface you may switch between several modes all of which offer the option of either automatically adding a line feed command (CHR$(10)) at the end of each line, or not adding it. This option may be selected   at   any   time   from within your programs so you can enjoy the best of both worlds.

First, let's find out if your printer has its line feed function on or off.   Try this sample program:

```
10   OPEN4,4,1
20   PRINT#4,"MY PRINTER WILL NOT
     PRINT ON THE SAME LINE TWICE."
30   PRINT#4,""TAB(16)"XXX":CLOSE4:END
```

If your printer X'ed out the word "NOT" then it will allow a return without a line feed.   If not, you may want to refer to your printer's instruction manual to see if there is a switch you can use to select this option, because this is the most flexible way to set up your printer.

C/?+G INTERNAL DIP SWITCH # 8
****

This dip switch manually controls the auto line feed function. It will allow you to manually override the software selection of this function provided by the previously mentioned open commands.

With this switch in the off position no auto line feeds will be sent to your printer under any circumstances. The interface will ignore the line feed information sent in the secondary addresses. So, for example, an open command of OPEN 4,4,7 will have the same effect as OPEN 4,4,8.

If this switch is on the interface will honor the auto line feed software selection as described in the preceeding section. So an open command of OPEN 4,4,7 would provide printing with auto line feed and OPEN 4,4,8 would print without line feed.

We would normally recommend that if you can turn off the line feed on your printer you should do so, then turn on dip switch # 8. This will provide you with the most flexible system. If you can't turn off the line feed function of your printer, then you should turn dip switch # 8 off. This will prevent double line feeds when using your printer with existing programs like word processors.

NORMAL PRINTING MODE
****

This is the mode of operation that you will use most of the time. This mode automatically changes Commodore's unusual ASCII to the standard ASCII format which is understood by normal printers. A chart on page # A45 will show you exactly what characters are converted to what if you need to know what is happening, but it all takes place automatically and you needn't know what's going on to make use of this function. What you DO need to know is that there are four options available in this mode.

1.   OPEN x,4 - This option sets the printer to print in the upper case only mode with a line feed added as we talked about in the last section. (OPEN X,4,Ø may also be used.)

2.   OPEN x,4,1 - This is the same as the above mode except that the line feed function is not implemented.

3.   OPEN x,4,7 - This option sets the printer in the upper/lower case mode and adds a line feed as before.

4.   OPEN x,4,8 - This is the same as above except this option is without the line feed function implemented.

NOTE: x is any file number (1 to 127)

Additionally,   there   are   four   other
important statements that apply to this mode.
You will have to be aware of these character
conversions if you plan to write your own
programs.   If you are using commercially
written programs however, these instructions
will do their job without your even knowing
they are there.

The first character change you should
know about is CHR$(17).   This   character is
produced by the **CURSOR DOWN** key, and it will
show up in a listing on your screen as a
reversed Q. When you send this character to
the printer it will shift you into the
upper/lower case print mode without having to
close and reopen the file. And, it has no
affect on the line feed function, if it was
on it'll stay on and visa-versa.

The second change is to CHR$(145).   This
is the **CURSOR UP** key, and it does the
opposite of the **CURSOR DOWN** key - it shifts
you into the upper case only mode.

Changes   three   and   four involve the
control codes sent to the printer to shift
out of the expanded print mode and to shift
into the condensed print mode.   If your
printer has these functions, then these codes
will be important to you.

A brief explanation of how the VIC
printer uses these codes will be helpful in
understanding what we change and why. The
reason we change these codes around is simply
so that you can run existing programs written
for your computer with the VIC printer
without any modifications. It does, however,
require you to remember what changes to make
when you are writing your own programs.

The VIC printer is set into the expanded
print mode (double size) by sending CHR$(14)
to the printer. It stays in that mode until
you send it a CHR$(15). Also, the VIC
printer has no provisions for condensed print
(small characters) at all so there are no
control codes to access this function.

On the other hand your printer (this
applies to Star Micronics, Epson, Radio Shack
and many others) probably will print only one
line in the expanded print mode and then
shift back to the normal print size
automatically so you will have to send
another CHR$(14) to print the next line in
the expanded print mode. If you want to go
back to normal size print in the middle of a
line the normal VIC command of CHR$(15) would
send you to a combination of expanded and
condensed print because most printers use
CHR$(15) to shift into the condensed print
mode. So we change CHR$(15) to CHR$(20)
which is the code most printers use to shift
back to normal size characters.

But that leaves us with the problem of
what to send to the printer to get into the
condensed print mode. If we send a CHR$(15)
the C/?+G changes it to a CHR$(20) so that
won't work.   But, if we changed CHR$(15) to
CHR$(20) it would make sense to change
CHR$(20) to CHR$(15) so that's what we did.
By the way, CHR$(18) is the code to revert
from condensed mode to normal mode and it is
changed by the C/?+G to cause the printer to
print reversed characters. See the appendix
section on trouble shooting and the example
program on the following page to see how we
solve that problem.

So, remember, CHR$(17) shifts the printer
into the upper and lower case mode; CHR$(145)
shifts the printer into the upper case only
mode; and CHR$(15) is swapped with CHR$(20).
All of these things happen in the NORMAL
PRINTING mode ONLY.

Try this program to see what your
printer can do. Most printers honor all of
these codes. If yours doesn't it will
probably just ignore the code and go on.

```
10   OPEN 4,4:OPEN5,4,5
20   PRINT#4,"THIS IS NORMAL UPPER CASE."
30   PRINT#4,"THIS IS "CHR$(17)"LOWER
     "CHR$(145) " AND UPPER CASE"
40   PRINT#4,"THESE ARE";
50   PRINT#4,CHR$(14)" EXPANDED";
60   PRINT#4,CHR$(15)" NORMAL";
70   PRINT#4,CHR$(14)CHR$(20)
     "EXPANDED/CONDENSED";
80   PRINT#4,CHR$(15)" AND CONDENSED";
90   PRINT#5,CHR$(18);
100  PRINT#4," CHARACTERS !"
110  PRINT#4,:CLOSE4:END
```

QUOTE MODE
****

The QUOTE MODE is automatically in operation whenever you are in the normal printing mode (secondary addresses 0,1,7 and 8). The quote mode is of most value when listing programs. A listing of a Commodore program usually contains some strange code symbols referring to functions such as color changes and cursor movements. These codes may mean other things to your printer however. For example if an Epson MX-80 printer was trying to list a program containing the HOME CURSOR symbol CHR$(19), it would stop dead because to the Epson CHR$(19) means stop printing until you are told to start again. So unless we make some changes I'm sure you would see how we could wind up with some strange looking program listings and unhappy programmers.

So, in the QUOTE MODE we have not only prevented disasterous listings, we made them easier to read. Instead of symbolic representation with reversed hearts and weird graphics, we substituted letters enclosed in brackets which are much more understandable in a listing.

If you look at a typical program listing you will see that whenever a cursor control code (cursor up, for example) is listed it is always part of a group of characters enclosed in quotation marks. When you are listing a

program the quotation marks tell the
"CARD/PRINT+G" that the group of characters
enclosed is a string to be printed during the
operation of a program. And the interface
should list them as such and include the
special listing codes as they are needed.

It is possible to fool the program into
thinking it is listing a program during the
running of a program by sending a CHR$(34) to
the printer as part of a print statement thus
enabling the QUOTE MODE. This will cause any
control codes to be converted to special
listing codes. This can be good or bad
depending on your intentions. The QUOTE MODE
is disabled either when another CHR$(34)
(quotation mark) or when a CHR$(13) (RETURN)
is sent to the printer. So be careful when
you are printing using CHR$(34) and quotation
marks.

This can create a bothersome situation
especially when sending dot addressable
graphics to the printer or using some word
processors. If you are sending dot graphics
to the printer we highly recommend using the
secondary address commands of ,4 or ,5 to
enable the TRANSPARENT MODE. When the
interface is in the TRANSPARENT MODE the
QUOTE MODE will be disabled.

Codes Used in Program Listings

CHR$ SENT	LISTING SYMBOL	SYMBOL DEFINITION
CHR$(1)	"{$1}"	Unknown Character
CHR$(2)	"{$2}"	Unknown Character
CHR$(3)	"{$3}"	Unknown Character
CHR$(4)	"{$4}"	Unknown Character
CHR$(5)	"{WHT}"	White
CHR$(6)	"{$6}"	Unknown Character
CHR$(7)	"{$7}"	Unknown Character
CHR$(8)	"{DISH}"	Disable Shift/ Commodore Key
CHR$(9)	"{ENSH}"	Enable Shift/ Commodore Key
CHR$(11)	"{$11}"	Unknown Character
CHR$(12)	"{$12}"	Unknown Character
CHR$(14)	"{SWLC}"	Shift to L/C
CHR$(15)	"{$15}"	Unknown Character
CHR$(16)	"{$16}"	Unknown Character
CHR$(17)	"{C/DN}"	Cursor Down
CHR$(18)	"{RVON}"	Reverse On
CHR$(19)	"{HOME}"	Home Cursor
CHR$(20)	"{DEL}"	Delete
CHR$(21)	"{$21}"	Unknown Character
CHR$(22)	"{$22}"	Unknown Charcater
CHR$(23)	"{$23}"	Unknown Character
CHR$(24)	"{$24}"	Unknown Character
CHR$(25)	"{$25}"	Unknown Character
CHR$(26)	"{$26}"	Unknown Character
CHR$(27)	"{$27}"	Unknown Character
CHR$(28)	"{RED}"	Red
CHR$(29)	"{C/RT}"	Cursor Right
CHR$(30)	"{GRN}"	Green
CHR$(31)	"{BLUE}"	Blue

Codes Used in Program Listings (continued)

CHR$(128)	"{$128}"	Unknown Character
CHR$(129)	"{ORNG}"	Orange
CHR$(130)	"{$130}"	Unknown Character
CHR$(131)	"{$131}"	Unknown Character
CHR$(132)	"{$132}"	Unknown Character
CHR$(133)	"{F1}"	F1 Function Key
CHR$(134)	"{F3}"	F3 Function Key
CHR$(135)	"{F5}"	F5 Function Key
CHR$(136)	"{F7}"	F7 Function Key
CHR$(137)	"{F2}"	F2 Function Key
CHR$(138)	"{F4}"	F4 Function Key
CHR$(139)	"{F6}"	F6 Function Key
CHR$(140)	"{F8}"	F8 Function Key
CHR$(141)	"{SHRT}"	Shifted Return
CHR$(142)	"{SWUC}"	Shift to U/C
CHR$(143)	"{$143}"	Unknown Character
CHR$(144)	"{BLK}"	Black
CHR$(145)	"{C/UP}"	Cursor Up
CHR$(146)	"{RVON}"	Reverse Off
CHR$(147)	"{CLR}"	Clear/Home
CHR$(148)	"{INS}"	Insert
CHR$(149)	"{BRN}"	Brown
CHR$(150)	"{LRED}"	Light Red
CHR$(151)	"{GRY1}"	Grey 1
CHR$(152)	"{GRY2}"	Grey 2
CHR$(153)	"{LGRN}"	Light Green
CHR$(154)	"{LBLU}"	Light Blue
CHR$(155)	"{GRY3}"	Grey 3
CHR$(156)	"{PURP}"	Purple
CHR$(157)	"{C/LF}"	Cursor Left
CHR$(158)	"{YELO}"	Yellow
CHR$(159)	"{CYAN}"	Cyan

TRANSPARENT MODE
****

In this mode you have the ability to pass
any   character   string   to   the   printer
unchanged.   This mode is primarily intended
for access to advanced graphics features
available on some printers and dedicated word
processors.   In   this   mode   whatever   the
computer sends the printer gets exactly as it
was sent.

You do have the option of line feed in
this mode if you should desire it. The
commands to access this mode are:

OPEN x,4,4   Transparent mode
               with line feed.

OPEN x,4,5   Transparent mode
               no line feed.

There are several program examples in the
appendix using the transparent mode. Examine
these examples and see how we used the
transparent modes of both the "CARD/?+G" and
your printer's special functions at the same
time.

DIP SWITCH # 7
****

Turning dip switch # 7 **off** will force the interface into the transparent mode and all software commands requesting other modes will be ignored. With the switch **on**, however, you will be allowed to use the software selections covered above.

This feature can be very useful when you are using some word processing programs that allow you to send corrected ASCII codes to the printer in conjunction with printer special function codes.

The TRANSPARENT MODE can also be locked in by the use of the LOCK MODE which is discussed in the next section. This software function can be used in place of the dip switch.

Experimentation will provide you with the best answers as to when and what programs to use this function with. Most of the time this switch should be turned on, but some graphics and word processing programs will work better with it off. In general the prefered position is ON.

LOCK MODE
****

The lock mode is provided to allow you to lock out any unwanted secondary address commands that might be sent to the interface by programs written to be used with only Commodore printers. Using this mode you will be able to prevent, for example, a program from sending a secondary address that adds an automatic line feed if your printer doesn't require one.

To use the lock mode all you need to do is add 20 to the secondary address that you want locked in. For example, if you want to lock in the TRANSPARENT MODE without line feed, you would add 20 to the secondary address normally used for that mode and send the command OPEN x,4,25. After sending the lock command you must send a print statement to complete the lock. For example you might send PRINT#4,"O.K."

There is only one way to quit the lock mode. You must "power down" the printer interface, this can be done by either turning your computer off for a moment or by unplugging momentarily the power cord that comes from the C/?+G and goes to the cassette port on your computer.

HEXIDECIMAL MODE
****

This mode will allow you to see exactly
what character values are being sent from the
computer to the interface. This mode will be
of most value when debugging a program that
is sending special characters to the printer.
For example, if you wrote a routine that sent
a formatted output including hi-res graphics
and other escape codes.

To use this optional feature all you need
to do is use the appropriate open command and
then run the program as you normally would.
Your printer will then print the hexidecimal
value of all characters sent by your program.
Even escape code sequences will be translated
to hex values and printed out (instead of
being acted upon) so you can see if you are
sending the right combination of characters.

For example here are some possible
characters that you might send, compared to
what you would see printed if you used the
HEXIDECIMAL MODE.   (Secondary address # 3)

CHR$(27)CHR$(69)"EMPHASIZED"
1B 45 34 45 4D 50 48 41 53 49 5A 45 44 34 ØD

CHR$(27)CHR$(66)CHR$(2)"12 CPI"
1B 42 Ø2 34 31 32 2Ø 43 50 49 34 ØD

CHR$(27)CHR$(75)CHR$(Ø)CHR$(1)CHR$(255)
1B 4B ØØ Ø1 FF ØD

CHARACTER MODE
****

When this mode is used all characters are printed as hi-res graphics characters. The formation and size of these characters is contained in the 8k ROM memory chip inside the C/?+G interface. Not to brag, but we feel that these characters are better looking than those in most printers and you may want to use them in some circumstances.

Additionally, Epson and Star Micronics printers use a different size for graphics characters than all other printers. Because of this, when intermixing text and graphics characters sometimes your columns may not line up. If you print all characters in hi-res graphics using this mode, all characters will be printed the same size and width. The CHARACTER MODE can be mixed in the same line with NORMAL PRINTING or any other mode. (NOTE: In the CHARACTER MODE on STAR and EPSON printers you will be limited to 60 characters per line.)

To enable the CHARACTER MODE use the open command OPENx,4,6. Closing the file (CLOSEx) and reopening the file with another secondary address will cancel the CHARACTER MODE.

Well, that's all there is. I hope this manual helped you to understand more about your   printer,   your   interface and your computer. Please read the information in the appendix   for   additional   explanations and examples of how to use the features of the C/?+G interface.   Here's wishing that all your programs run the first time.

Our Best To You,

CARDCO,   Inc.
300 S. Topeka
Wichita, Ks.
      67202

CARD/PRINT +G - APPENDIX TO MANUAL
CARDCO, Inc.   -   (316) 267-6525

DIP SWITCH SETTINGS
****

To properly set up your interface for use
with your printer you must set the DIP
SWITCHES inside the interface to provide the
proper configuration for your printer. With
the interface disconnected from your system,
remove the four screws holding the case
together, seperate the case and set the
switches in acccordance with the following
chart. Now reassemble the interface and
proceed with the normal hook up as described
in the beginning of the instruction manual.

Switch:	1	2	3	4	5	6	7	8
Epson	on	off	on	xx	on	off	xx	xx
Prowriter	on	on	off	xx	off	on	xx	xx
Okidata (ALL)	off	off	on	xx	on	on	xx	xx
Siekosha	off	on	off	xx	off	on	xx	xx
All Others	on	on	on	xx	on	on	xx	xx

xx=optional user choice see following page.

Epson type printers: This group includes all
current Epson printers, Star Micronics Delta,
Radix and Gemini 10x/15x, Mannesman Tally
Spirit and MT-160, the BMC-80, all Panasonic
KXP series, all Smith Corona DP series.

Prowriter type printers: This group includes
the Prowriter 8510, C-ITOH 8510, NEC 8023 amd
the New HOT DOT.

Siekosha type printers: This group includes
the Siekosha GP-100, Axiom GX-100 and the
Gorilla Banana.

Optional Switch Positions
****

The function of the additional switches are
as follows.

Switch # 4 - Device # selection

ON sets the printer to device #4

OFF sets the printer to device #5

Switch # 7 - ASCII Correction selection

ON allows software selection of ASCII
correction.

OFF locks in the transparent (no ASCII
correction) mode

Switch # 8 - Auto line feed selection

ON allows software selection of the auto
line feed functions

OFF locks the unit in the non-auto line
feed mode

SPECIAL PRINTER CODES
****

We have found that most printer instruction manuals leave something to be desired in the area of informing the user about the use of special printer functions. For general use these guide lines should be of some help. (Please refer to your printer's instruction manual)

FUNCTION CODES.

These codes are always less than 32 (decimal) or between 128 and 160. These codes are usually listed as something like:

SO   14/142   ØE/8E   Double Wide
                         Characters

This translates as:

SO   This is the name they call the function for short.

14/142   This is the number (or numbers) that must be sent to the printer to enable this function. If two numbers are given you may send either of these numbers. This number must be sent as a character string (ie. CHR$(14))

ØE/8E   This is the hexidecimal value of the above number.

--   This should explain what this function does.

THE ESCAPE CODE and SPECIAL FUNCTION CODES
****

THE ESCAPE CODE (IMPORTANT)

If your printer has any special codes that it honors other than the function codes which were covered above they will always be used in conjunction with this code. This code tells your printer that you are sending it a special code and that the printer is to act on this code and not treat it as a normal character and print it. This code is called the ESCAPE CODE. It is always sent to the printer as CHR$(27). Whenever you see ESC or ESCAPE that means send CHR$(27) and follow it with another code.

SPECIAL FUNCTION CODES.

These are the special function codes that your printer allows. These codes are always preceded by the escape code which is always sent as CHR$(27). Because these codes usually are assigned the same values as the upper case alphabet you must be careful when sending them "THROUGH" our interface because in some modes the interface changes these values. These codes are usually listed in your printer manual in a cryptic format. We will try to explain how to use these codes.

The codes are usually shown like this:

ESC   E   69   45   emphasize print

This translates to:

ESC   E   Send the printer the escape code
            CHR$(27) and then send it an E.

69   The decimal value of "E" which
            can be sent to the printer as
            CHR$(69).

45   The hexidecimal value of "E".

---   This should be an explanation of
            the special function that is done
            when this command is executed.

    When   sending   these codes to the printer
try to use this format:

PRINT#4,CHR$(27)"E"

The "E"   must   be   upper   case,   if   you   are
printing   in   the   upper/lower   case   mode
(secondary address 7 or 8).

If you are using a word processor   that   does
not   allow   you   to   send letter codes to the
printer, and requires only numbers,   you   can
send   the correct number by adding 128 to the
number shown in your printer   manual   if   the
letter   is   supposed   to   be   an   upper case
character.

Some control codes require more than one
character after the ESCAPE CODE for example:

ESC Q n   81 n   51 n   Set Right Margin.

In this example the printer "sees" this as:

CHR$(27)"Q"CHR$(70)

** OR **

CHR$(27) - Ah Ha, This is an escape code, so
            I should not print the next char-
            acter, because the next character
            will be an instruction for me.

"Q"   This instruction tells me to set
            the right hand margin. But I need
            to wait for the next character to
            tell me where to set the margin.

CHR$(70)   This tells me that the right
            margin is to be set to the 70th
            position. And that's all the in-
            formation I need, so I go back
            into my normal operation and put
            the next character on the paper.

With a little practice and reading your
printer's instructions you should be able to
make it do all of its tricks for you.

COMMANDS THAT DON'T WORK
?????????????????????????

As we mentioned in the text of this
manual, there are several abnormalities in
the Commodore computers that affect printing
functions. We will cover those that we know
about and if you find any more please let us
know so we can add them to updates of this
manual for future Commodore owners.

#1. The first oddity is the format that must
    be used to close a file from the CMD#
    mode.   It seems that the only statement
    that will work consistently is:

                PRINT#x:CLOSEx

    Where "x" is the file number to be
    closed.

        We   have   no   idea   why   this is
    necessary, but a simple   CLOSE(x)
    statement doesn't seem to work in all
    cases.

#2. Another function that doesn't work right
    is the SPC function. If you try to put
    this into a program:

                PRINT#4,SPC(20)

    you will get a syntax error. This is a
    bug in the Commodore computer because
    that should be a legal statement.   THE
    ONLY WAY THIS STATEMENT WILL WORK IS:

                PRINT#4,""SPC(20)

#3. Another function that doesn't work right
is the TAB function. If you try to put
this into a program:

PRINT#4,TAB(20)

you will get a syntax error. This is a
bug in the Commodore computer because
that should be a legal statement. THE
ONLY WAY THIS STATEMENT WILL WORK IS:

PRINT#4,""TAB(20)

This allows the TAB function to work,
but not very well. All that will happen
is that the printer will move over 20
spaces from the last printed character.

There are four solutions to this
problem and some will work with some
printers while another may be required
for your printer. Experimentation will
provide the best solution for your
system, so we will give you several
options.

1. This is the simplest form of tabbing
and it works on all printers that are
specified for use with the C/?+G.
Commodore provides a simple tab
function in their printers which we
have duplicated in the C/?+G. This
tab function has its limitations, but
should work for most applications.
The command to move to a tab position
is CHR$(16) followed by a two digit
decimal number of the desired tab
location.

The tab location is an absolute value. That means, no matter where you are on a specific print line if you tell the printer to tab to location 17 (PRINT#4,CHR$(16)"17";) it will move the print head and start printing at position 17 even if you have already printed past that position. A sample program to do tabbing using this command can be found in the section on COMMODORE SPECIAL PRINTER CODES later in this appendix.

Remember, the CHR$(16) must always be followed by a two digit decimal number (ie. CHR$(16)"Ø5" or CHR$(16)"2Ø"). The string of characters you want to print may then be sent right after the two numbers.

(ie. CHR$(16)"Ø8HI BILL").

If you wish to tab to a calculated position you will need to do a little extra work. An example of this form of tabbing also will be shown in a sample program later in this manual.

2. If your printer requires the line feed option then this is the easiest solution for you. To do tab functions, close the file you are using; reopen it without the line feed function and then print each item to be tabbed as a separate print statement. But, be sure to print CHR$(1Ø) to advance the paper to the next line after the last item you want printed on each line. Try this:

SAMPLE TAB PROGRAM # 1
****

```
10   OPEN 4,4: FOR I = 1 to 4

20   PRINT#4,"THIS IS LINE #"I:NEXT I

30   CLOSE4:OPEN4,4,1

40   FOR I = 1 TO 4

50   REM SEVEN TABS AT 10, 20, 30...

60   PRINT#4, ""TAB(10)I*10

70   PRINT#4, ""TAB(20)I*20

80   PRINT#4, ""TAB(30)I*30

90   PRINT#4, ""TAB(40)I*40

100  PRINT#4, ""TAB(50)I*50

110  PRINT#4, ""TAB(60)I*60

120  PRINT#4, ""TAB(70)I*70

130  PRINT#4,CHR$(10)

140  NEXT I : CLOSE4:END
```

This will work with most Star, Epson, Okidata
and other printers.

3. If that doesn't work on your printer then try looking in your printer manual to see if the printer itself has the ability to provide the tab function. In the Star GEMINI 10 the tabs are preset to every tenth position and accessed by printing CHR$(9). But you can set your own if you like. The code to set the tabs is CHR$(27)CHR$(68) followed by your desired tab locations given as CHR$(x) as many times as you need tabs, and then ended with CHR$(0). This tells the printer there are no more tabs and to return to normal printing. In the Epson printers tabbing is the same as the Star.

   The Okidata Microline 82 & 83 series printers do not allow for horizontal tab, but the Microline 84, 92 and 93 do. These are implemented as above with CHR$(9), but are set with CHR$(27) CHR(9) then your tabs as three digit numbers (IE, "002" or "002,020,042").

4. As a last resort you can construct your own tab function by printing everything as a string and tabbing from the end of the last item printed the desired distance minus the length of the string just printed. This is a last resort but will always work.

   Here is a sample of how to do it:

PROGRAM EXAMPLE TO DO TABBING # 2
=================================

```
10      OPEN4,4
20      FOR I = 0 TO 10
30      READ A$,B$
40      A=A+I*I
50      B=B+I*B
60      REM FOUR TABS AT 10,30,50,70
70      PRINT#4,""TAB(10)A$;
80      PRINT#4,""TAB(20-LEN(A$))A;
90      PRINT#4,""TAB(20-LEN(STR$(A)))B$;
100     PRINT#4,""TAB(20-LEN(B$))B
110     NEXTI:END
120     DATA THE,NEW,CARDCO,INTERFACE
130     DATA E.J.LIPPERT,PRES,CARDCO,INC.
140     DATA BRECK RICKETTS,VP,CARDCO,INC.
150     DATA CARD/?,CARDBOARD/6,CARDETTE,A
160     DATA CARDBOARD/3,CARDRITER,KS.,MN.
```

　　　In this sample we will print a mixture of strings and numbers and tab for even spacing. Note that the numbers must be   converted   to string format   for   this   to work unless the numbers are all the same length. If you   use for   next loops for your printing this is not as difficult as it would seem.   And   if   you take   the   time to use this method it is fool proof and will work on any printer with   any program.

WORD PROCESSORS
****

Some word processors offer additional features and special codes when you specify that you are using a NON-Commodore printer. Since the C/?+G simulates a Commodore printer in normal print modes it will cause a conflict if you take this option. So to allow you to take advantage of special word processor functions, you should use the following open command sequence before calling up your word processor:

OPEN4,4,25:PRINT#4,"LOCK":CLOSE4   <RETURN>

This will lock the interface in the non-Commodore mode and allow the word processor to control all ASCII conversion and line feed functions. You may now specify the type of printer you have when the word processor prompts you for this information.

This command is recommended for use with "EASY SCRIPT", "SCRIPT/64" and "WORDPRO 3 PLUS" word processors.

Be aware that once you are locked in a mode the only way to unlock the "CARD/?" is to power-down. The easiest way to power-down is to unplug the power line that goes to the cassette port.

QUICK SCREEN DUMP WITH COMMODORE GRAPHICS
****

This screen dump can be used in any basic program to copy the contents of any screen (except hi-res screens) to any printer. It would work fine to copy a screen of numbers from a check book program or the instructions from a game or some other program.

To use this function add these lines to the program then put the statement "GOSUB 63999" in the program at the point (or points) at which you wish to dump the screen to the printer, and then :

```
63000     REM * * * SCREEN DUMP

63010     REM * * * BY E.J. LIPPERT II

63030     OPEN4,4:CG = PEEK (36869)

63040     IF(CG=242)OR(CG=194)THEN
          CLOSE4:OPEN4,4,7

63050     SC = 4*(PEEK(36866)AND 128)+
          64*(PEEK(36869)AND112)

63060     FOR I0 = 0 TO 999

63070     C0 = PEEK(SC+I0):IFC0>128THEN
          C0=C0-128:CR=1

63080     GOSUB63300

63090     IFCR=1THENPRINT#4,CHR$(18)
          CHR$(A0)CHR$(146);:CR=0:GOTO
          63110
```

```
63100     PRINT#4,CHR$(AØ);:LØ = LØ +1
63110     LØ=LØ+1
63200     IF LØ=22 THEN PRINT#4," ":LØ=Ø

63210     NEXT IØ:CLOSE4:RETURN


63300     IF CØ<32 THEN AØ=CØ+64:RETURN

63310     IF CØ<64 THEN AØ=CØ:RETURN

63320     IF CØ<96 THEN AØ=CØ+32:RETURN

63330     IF CØ<128 THEN AØ=CØ+64:RETURN
63340     AØ=32:RETURN

63999     GOTO63000
```

To change this program to run on the C-64:

```
63030     OPEN4,4:CG = PEEK(53272)

63040     IFCG=23THENCLOSE4:OPEN4,4,7
63050     SC = 1024

63060     FOR IØ = Ø TO 999

63200     IF LØ=40 THEN PRINT #4," ":
          LØ=Ø
```

Adding these lines will allow you to fill up a screen with text or graphics, and then press the {F1} key to print the screen.

```
10      PRINT"<CH>"

20      GET A$:  IF A$ = "" THEN 20

30      IF A$ = CHR$(133) THEN GOSUB
        63999

40      PRINT A$;:GOTO 20
```

You can use this program to fill the screen with characters and graphics, then whenever you press the {F1} function key it will go to your subroutine and dump your screen contents to your printer.

VIC-20 HIGH RESOLUTION SCREEN DUMP
****

This is a very unusual screen dump. It may give you a new perspective on how your printer sees your Commodore computer. To use this screen dump just insert "GOSUB 63999", or "GOSUB 62999" for a reversed image, where ever you want a snapshot of your screen. This is in basic so it is somewhat slow but it'll get the job done. An examination of this program will probably teach you a few things about programming.

PROGRAM BY: E.J. LIPPERT II

```
62999     RV=1

63000     C0=PEEK(36869)

63010     SC=4*(PEEK(36866)AND128)
          +64*(PEEK(36869)AND112)

63020     IF C0 > 239 THEN C0=C0-240:
          GOTO63040

63030     C0=C0-192

63040     IF C0 < 3 THEN CG = 32768+
          (C0* 1024): GOTO 63060

63050     IF C0 > 11 THEN CG = 4096+
          ((C0-12)* 1024): GOTO 63060

63060     OPEN4,4,4: PRINT#4,CHR$(10)
          CHR$(10)
```

```
63070      PRINT#4,CHR$(27)CHR$(64)

63080      PRINT#4,CHR$(27)CHR$(51)
           CHR$(12)" "

63090      FOR I1 = 0 TO 21

63100      PRINT#4,"          "CHR$(27)
           CHR$(76)CHR$(112)CHR$(1);

63110      FOR I2 = 0 to 22

63120      C1 = PEEK(SC+(22*(22-I2))+I1)

63130      FOR I3 = 0 TO 7

63140      C2 = PEEK(CG+(C1*8)+(7-I3)):
           IF RV=1 THEN C2 = 255 - C2

63150      PRINT#4,CHR$(C2)CHR$(C2);

63160      NEXT I3

63180      NEXT I2 : PRINT#4,CHR$(10)

63190      NEXT I1

63200      PRINT#4,CHR$(10)

63210      PRINT#4,CHR$(27)CHR$(64)

63220      CLOSE4 : RETURN

63999      GOTO 63000
```

The preceding version of the program was written for the STAR MICRONICS GEMINI 10x/15x, EPSON MX-80/100 with graftrax, Panasonic KXP-1090, Smith Corona DP-200/DP-300, Mannesman Talley SPIRIT/160, and BMC-80 printers. To modify it for the Prowriter, C ITOH 8510 and NEC 8023 you will have to change these lines to read:

```
63080     PRINT#4,CHR$(27)CHR$(84)"16";

63100     PRINT#4,"              "CHR$(27)
          CHR$(83)"0368";

63180     NEXT I2 : PRINT#4,CHR$(10);

63210     DELETE THIS LINE
```

And that should have you running on your printer.

THIS PROGRAM WILL NOT RUN ON AN OKIDATA, SIEKOSHA, AXIOM OR GORILLA BANANA PRINTERS. Due to their ability to accept only 7 bit graphics codes, the changes required would be too extensive to be included in this manual.

"CARD/PRINT PIN OUT DIAGRAM
****

This is a standard Centronics type parallel
pin out.

Pin #   Function
==

1   data strobe (data ready to print)
2   8 bit ASCII - data bit Ø
3   8 bit ASCII - data bit 1
4   8 bit ASCII - data bit 2
5   8 bit ASCII - data bit 3
6   8 bit ASCII - data bit 4
7   8 bit ASCII - data bit 5
8   8 bit ASCII - data bit 6
9   8 bit ASCII - data bit 7
1Ø   not used
11   busy line (printer busy)
12-13   grounded
14   n/c
15-17   grounded
18   n/c
19-3Ø   ground returns
31   prime output (printer reset)
32   not used

COMMODORE SPECIAL PRINTER CODES
****

These codes are the same format as the
Commodore VIC 1515/1525/1526 printer codes.
The CARDPRINT/+G honors and obeys all these
Commodore special functions only when in the
NORMAL PRINT MODE (secondary addresses 0,1,7
& 8)and the CHARACTER PRINT MODE (secondary
address 6).

CHR$(8) - DOT ADDRESSABLE GRAPHICS MODE

        Sending this code will cause all data
following the code to be printed as dot
addressable graphics characters until it
is terminated by sending a CHR$(14) or
CHR$(15). This function is identical to
the Commodore dot graphics format. All
character string (CHR$) values must be
greater than 127. Sending a CHR$(128) to
the printer in this mode will result in a
blank (null character) being printed at
the current character position. Sending
a CHR$(255) to the printer in this mode
will result in a solid vertical line 7
dots high being printed at the current
character position. Other CHR$ values
will result in other combinations of dots
being printed at the current character
position.   See the next page for an
example program and an explanation of how
hi-res dot graphics are constructed.

EXAMPLE PROGRAM:
```
10 OPEN4,4: PRINT#4,CHR$(8);:FORJ=0TO4
20 FORI=128TO255:PRINT#4,CHR$(I);:NEXT
30 PRINT#4," ";:NEXT:PRINT#4,CHR$(15):
   CLOSE4
50 OPEN4,4: PRINT#4: PRINT#4,CHR$(8);
60 READA:IFA=-1THENPRINT#4,CHR$(15):
   CLOSE4:END
70 PRINT#4,CHR$(A);:GOTO60
80 DATA 156,162,201,213,213,213,208,
   208,219,195,187,-1
```

This program will print some hi-res dot graphics, then line feed and print a hi-res custom character five times. The information used to make this hi-res character is contained in the data statements in line 80. Compare these data bytes to the chart below and you will see how to create your own hi-res graphics.

BIT VALUE											
1			X	X	X	X			X	X	X
2		X							X	X	X
4	X			X	X	X					
8	X		X						X		X
16	X			X	X	X	X	X	X		X
32		X									X
64			X	X	X	X	X	X	X	X	
TOTAL	28	34	73	85	85	85	80	80	91	67	59
+128	128	128	128	128	128	128	128	128	128	128	128
CHR$ VALUE	156	162	201	213	213	213	208	208	219	195	187

In the example chart on the previous page you should notice that each vertical row of dots corresponds to one of the data statement values in line 80 of the example program. The Commodore printer uses a seven dot vertical pattern and each dot position in the pattern corresponds to a power of two as shown in the chart. Adding the numbers up for each position you want a dot at and then adding 128 to the total will give you the correct CHR$ value to send to the C/?+G to obtain the dot pattern that you want.

PROGRAMMERS NOTE: Within the C/?+G several conversions take place to accomplish this graphics function. The C/?+G will work with many different printers but they all use one of four graphics routines. This is how each works:

EPSON type printers will be sent graphics data one byte at a time using the format:
    CHR$(27)"K"CHR$(0)CHR$(1)CHR$(data);

C-ITOH type printers will be sent graphics data one byte at a time using the format:
        CHR$(27)"S001"CHR$(data);

OKIDATA type printers will be sent a CHR$(3) to put them in the dot graphics mode then on receiving a CHR$(15) the C/?G will send a CHR$(3)CHR$(2) which causes these printers to return to the normal printing mode.

AXIOM/BANANA type printers will be sent a CHR$(8) to put them in the dot graphics mode then on receiving a CHR$(15) the C/?G will send a CHR$(20) which causes these printers to return to the normal printing mode.

CHR$(14) - DOUBLE WIDTH CHARACTER MODE

This code puts your printer into the DOUBLE WIDTH CHARACTER MODE. The printer will print double wide characters until this mode is cancelled by sending a CHR$(15).

EXAMPLE PROGRAM:
```
10 OPEN4,4: PRINT#4,"THIS IS A ";
20 PRINT#4,CHR$(14)"DOUBLE WIDE";
30 PRINT#4,CHR$(15)" TEST":CLOSE4
```

CHR$(15) - RETURN TO NORMAL PRINT MODE

This code cancels the DOUBLE WIDTH CHARACTER MODE and the DOT ADDRESSABLE GRAPHICS MODE. (See the above example.)

PROGRAMMERS NOTE: These functions are accomplished by translation inside the interface. The position of the dip switches tell the interface what printer you are using, and the interface sends it the required code. The chart below will tell you what codes are being sent to what printers.

DESIRED FUNCTION	CHR$(14)	CHR$(15)
EPSON/STAR	CHR$(14)	CHR$(20)
PANASONIC		
BMC/MANNESMAN		
PROWRITER	CHR$(14)	CHR$(15)
C-ITOH/NEC		
AXIOM/BANANA		
OKIDATA	CHR$(31)	CHR$(30)

CHR$(16) – CHARACTER TAB MODE

This is the control code that enables the Tab function. This code works identically to the Commodore Tab Function. After sending the CHR$(16) you should send a two character (numeric) tab position. This two character code will tell the printer what character position (from 1 to 255) to start printing at.

EXAMPLE PROGRAM:
```
10 OPEN4,4:PRINT#4,CHR$(16)"40TEST"
20 FORJ=1TO7:READ A$,B$
30 PRINT#4,A$B$;:NEXT:PRINT#4
40 FORJ=1TO7:READ B$
50 PRINT#4,CHR$(J+48)"0"B$;:NEXT
60 DATA 30,TAB,60,OR,20,CAN,70,RIGHT
70 DATA 50,LEFT,10,WE,40,TO
80 DATA OR,WE,CAN,TAB,BY,THE,NUMBERS
```

This will cause the word TEST to be printed starting at the 40th character position from the left edge of the paper, and demonstrate two additional methods of tabbing.

PROGRAMMERS NOTE: To perform this function the C/?+G sends the printer a CHR$(13) to move the print head to the start of the line, then it sends the required number of spaces (CHR$(32)) to move the print head to the position requested by the next two character strings. The formula used to determine the number of spaces to be sent is $\# = ((VAL(C1)-48)*10) + VAL(C2)-48$. Where C1 and C2 are the first and second characters following the CHR$(16).

CHR$(17) - UPPER/LOWER CASE PRINTING MODE
          (CURSOR DOWN MODE)

     This code puts your printer into the
UPPER/LOWER CASE   PRINTING   MODE   the
printer will print upper and lower case
with business graphics until this mode is
cancelled by sending a CHR$(145).

EXAMPLE PROGRAM:
     10 OPEN4,4: PRINT#4,"THIS IS A TEST ";
     20 PRINT#4,CHR$(17)"OF LOWER CASE ";
     30 PRINT#4,CHR$(145)"PRINT MODE":CLOSE4

PROGRAMMERS NOTE: To do this function
the C/?+G simply swaps the secondary
address it uses to either 0, or 7.

CHR$(18) - REVERSE CHARACTER PRINT MODE

     This code puts your printer into the
REVERSE   CHARACTER   PRINT   MODE.   The
printer will print reversed characters
until this mode is cancelled by a
CHR$(146).

EXAMPLE PROGRAM:
     10 OPEN4,4: PRINT#4,"THIS IS A TEST ";
     20 PRINT#4,"OF "CHR$(18)"REVERSE";
     30 PRINT#4,CHR$(146)" PRINTING":CLOSE4

PROGRAMMERS NOTE: Reversed characters are
sent from the character ROM inside the C/?+G.
They are sent as 8 byte long hi-res graphics
characters using the hi-res function of your
printer.   (See   CHR$(8)   function   for a
description of these codes.)

CHR$(26) – REPEAT GRAPHICS DATA MODE

This code can only be sent when in
the CHR$(8) graphics mode. This code,
when sent, must be followed by a value
sent as a character string value (CHR$(Ø)
to CHR$(255)). The code will cause the
next character string value sent to be
repeated the number of times specified by
the character string value up to 255
times.

EXAMPLE PROGRAM:
```
1Ø OPEN4,4: PRINT#4,CHR$(8);
2Ø PRINT#4,CHR$(26)CHR$(1ØØ)CHR$(255)
3Ø PRINT#4:PRINT#4:PRINT#4,CHR$(8)
4Ø FORI=1TO6:PRINT#4,CHR$(26);
5Ø PRINT#4,CHR$(I*8)CHR$(127+(2~(I+1)));
6Ø NEXT:PRINT#4,CHR$(15):CLOSE4
```

This program will cause the character
string 255 to be printed one hundred
times (this is done in line 2Ø) as a dot
graphics character. This will result in
a horizontal bar being printed by your
printer. Then on the next line it will
do a progression of graphics data (this
is done in lines 4Ø and 5Ø) to
demonstrate other uses of the CHR$(26)
COMMAND.

PROGRAMMERS NOTE: This function is done
totally inside the C/?+G. It is done by
simply storing the ASCII value that follows
the CHR$(26) in a temporary buffer and then
sending the next character received to the
printer as many times as requested by the
number stored in the buffer.

CHR$(27) - DOT GRAPHICS TAB MODE

Sending this code puts your printer into the hi-res graphics tab mode. This allows you to position the print head at a specific dot addressed print position. This code must be followed by a CHR$(16) and then followed by two other CHR$ values. The two character strings that follow the CHR$(27) CHR$(16) series will be the high byte and low byte of the desired dot position. Your printer will print a line up to 80 characters wide, and each character is 8 bytes wide, so there are (80X8=640) up to 640 potential dot locations on each line. The format for this command is:

CHR$(27) CHR$(16) CHR$(C1) CHR$(C2)

To calculate the values that should be sent after the CHR$(27) use the following formula:

C1 = INTERGER (Desired Position/256)
C2 = Desired Position - (minus) (C1*256)

EXAMPLE PROGRAM:
```
10 OPEN4,4:PRINT#4,CHR$(27)CHR$(16)
   CHR$(1)CHR$(35)"HERE":PRINT#4
20 FORI=1TO32:PRINT#4,I;CHR$(8);:READA
30 PRINT#4,I;CHR$(27)CHR$(16);
40 C1=INT(A/256):C2=A-(C1*256)
50 PRINT#4,CHR$(C1)CHR$(C2);A
60 DATA 50,52,88,89,90,100,135,186,232,
   233,234,235,237,240,244,249,254,261
70 DATA 311,440,500,501,502,504,508,
   516,532,564,574,584,594,604
```

This program will cause the print head to move to the ((1*256)+35) 291st dot position and print the word HERE starting at that point. Then it will print a simple example of a horizontal bar chart showing the level of high resolution that is available in this mode.

PROGRAMMERS NOTE: This function is done in a similar manner as the CHR$(16) character tab function. Instead of the two digit numeric value however, this function uses the next two byte values as the position indicator. The C/?+G then sends a CHR$(13) to position the print head at the start of the line. Then it sends the proper number of CHR$(Ø)s to position the print head at the desired print position. Be aware that because we print a string of CHR$(Ø)s you can send a value greater than 64Ø. By sending, for example, CHR$(255) CHR$(255) you can tab 65535 (265*256-1) dot positions. This will place you 1Ø2 lines down and on the 256th dot position on that line. (By the way the two digit number used in the CHR$(16) character tab function can also be used to exceed the number of character positions on a line by using characters other than decimal digits.)

Also, unlike most tab functions both the C/?+G tab functions will allow you to tab backwards to a print position to the left of your present print position. We're not quite sure what you might need this feature for but don't say we didn't tell you about it.

CHR$(145) – UPPER CASE/GRAPHICS PRINT MODE
          (CURSOR UP MODE)

    This code puts your printer into   the
UPPER CASE/GRAPHICS PRINTING MODE.   The
printer will print upper case   with   full
graphics   until   this   mode is changed by
sending a CHR$(17).   (See   CHR$(17)   for
the example program.)

CHR$(146)   –   REVERSE   OFF – NORMAL PRINT
MODE

    This code puts your printer into   the
NORMAL   PRINT MODE cancelling the REVERSE
CHARACTER PRINT MODE.   The   printer   will
print   non-reversed characters until this
mode is reinstated by sending a CHR$(18).
(See CHR$(18) for an example program.)

TROUBLE SHOOTING
****

This section is here to help you solve
the most common problems you may have with
the C/?+G interface. Please consult the
following pages before you pull your hair
out. We at Cardco want you to be satisfied
with our interface and want to help you if
you'll let us. This section is written in a
question answer format to make solving your
problem easier. If after you have tried all
the following suggestions and your interface
still will not do what you want it to, please
feel free to write or call us at:

CARDCO, Inc.
300 So Topeka
Wichita, Ks.
      67202

PHONE − (316) 267-6525

It is possible to get an interface that
doesn't work. If you have a defective unit
we will replace it for you or you may wish to
return it to the store from which you
purchased it for an immediate replacement.
If you suspect that our product is defective
and wish to return it to us for replacement
send it to us at the above address with your
purchase receipt. We will send your
replacement to you by UPS. Under no
circumstances will a replacement be sent
before the defective unit is received.

IMPORTANT – READ THIS PAGE
****

We have found that over 90% of all problems are a result of improper installation of the interface. Please be sure that the following three items have been properly complied with.

FIRST, be sure that the dip switches inside your printer are set properly. Refer to the charts on the next two pages for assistance.

SECOND, be sure that the dip switches inside the C/?+G are set properly for your printer. Refer to the section on setting the dip switches starting on page Al of this appendix.

THIRD, Be sure that the interface has been properly installed on your system and that the power supply line is properly inserted into the cassette port on the rear on your computer. Refer to the HOOK UP PROCEDURES section at the beginning of this manual.

FOURTH, be sure that you have turned on the components of your system in the proper order. The proper sequence is: printer first, computer second, pause and wait for the screen to come up with the CBM basic message, last turn on your disk drive(s) and any other accessories.

Question:

Why can't I get my Prowriter/C-Itoh 8510/NEC-8023 to print what I want it to or do the correct line feed functions?

Answer:

The first thing you have to do is to make sure the dip switches inside your printer are set properly. The proper settings are as follows:

Bank #1

8	7	6	5	4	3	2	1
off	on	on	off	off	off	on	off

Bank #2

8	7	6	5	4	3	2	1
off	on	off	off	off	off	off	on

NOTE: Some dip switches are marked OPEN and CLOSED. A switch is OFF if it is OPEN and ON if it is CLOSED.

NOTE: The preceding dip switch settings are for the internal dip switches in the Prowriter, C-Itoh 8510 and NEC 8023 printers only.

Question:

In what position should the dip switches
in my printer be set?

Answer:

Normally you   should   leave your printer dip
switches in   their   original position, most
printers will   work   with the C/?+G. But if
for some reason your printer won't work with
the   C/?+G   then   you   should   try the switch
positions listed   below. **(NOTE: These are
settings   for   the   dip switches   in your
printer, not the C/?+G interface.)**

Bank #1	Epson (all)	Star Gemini 1ØX
switch 1	off	on
switch 2	either	off
switch 3	off	off
switch 4	off	off
switch 5	off	n/a
switch 6	on	n/a
switch 7	on	n/a
switch 8	on	n/a

Bank #2		
switch 1	either	n/a
switch 2	either	n/a
switch 3	off	n/a
switch 4	off	n/a
switch 5-8	n/a	n/a

If your printer is not listed then please
read your   printer manual to get the proper
dip switch settings.

Question:

My printer isn't listed in your manual, what dip switch settings do I use?

Answer:

If your type of printer is not listed do not despair. Refer to the instruction manual that came with your printer to set the dip switches in the printer. These switches should be set for standard parallel operation without line feed.

As far as the switches in the C/?+G, if your printer is a letter quality printer you will want all the dip switches on. If your printer is a dot matrix then you may want to try all the different settings. Chances are you will find one that will work for your type of printer. (Although we only guarantee that the C/?+G will work with the dot matrix printers we have listed.) Turning all the switches on will also work with any dot matrix printer and will allow you to print but in this mode you will not get any of the Commodore graphics characters or Special Commodore print command functions.

If your printer still won't print go to the first page of this section on trouble shooting and try the suggestions there.

Question:

My C/?+G is not working properly with my printer and I can't get it to do everything I want it to do. What do I do?

Answer:

Assuming that you have followed the instructions on the previous page, the thing you may need to look at is which secondary address you are using. You need to make sure that you are using the proper address to achieve your desired result. For example if you want upper/lower case printing without line feed you want a secondary address of seven (7). If you're not using a secondary address at all then we may have solved you problem.(Check the section in this manual that deals with secondary addresses.) Also you should refer to the sections on special printer codes, escape codes and Commodore special printer codes in this appendix.

Question:

Why can't I get my cursor back?

Answer:

If you are sure that you have followed the IMPORTANT information at the beginning of this section and are sure your printer is **ON LINE** then you probably have a defective interface.

Question:

Why won't my C/?+G print in upper and lower case?

Answer:

Assuming that the dip switches inside the interface are set properly, what you need to check is which secondary address you are using. If you're not using a secondary address, you probably need one and that should solve you problem. (Check the section in this manual that deals with secondary addresses.)

Question:

I can't seem to get rid of line feed when I need to! AND/OR I keep getting double line spacing on all (some) of my printing!

Answer:

Assuming that the dip switches inside the interface are set properly, the first thing you need to look at is which secondary address are you using. You will need a secondary address that will control your line feed. If you're not using a secondary address at all then this should solve your problem.(Check the section in this manual that deals with secondary addresses.)

Question:

I can't seem to get all the special CHR$
values or Commodore characters to print on my
printer.

Answer:

The first thing you need to look at is
which secondary address you are using. You
will want a secondary address of either
null(Ø), one(1), six(6), seven(7) or eight(8)
to get the Commodore special functions and
Commodore graphics characters you want.   If
you want to use some special functions of
your printer you may wish to use secondary
adresses   four(4)   or five(5) so that no
changes are made to your codes by   the
interface. (Check the section in this manual
that deals with secondary addresses.)

If you need to use both Special Commodore
functions   and   graphics as well as your
printer's special features in   the   same
program it may be necessary to open several
files to your printer.   See the next two
questions for an example of this.

Question:

How do I get into the condensed printing mode with an Epson/Star type printer?

Answer:

To accommodate the standardized Commodore commands CHR$(15) and CHR$(20) are swapped inside the C/?+G. If you send a CHR$(15) the printer gets a CHR$(20) and if you send a CHR$(20) the printer gets a CHR$(15) (see the character conversion chart at the rear of the appendix.) An Epson/Star type printer requires a CHR$(15) to enter the condensed mode so you should send a CHR$(20) from your program. NOTE: This conversion is not done in the transparent mode.

Question:

How do I get back to normal printing from the condensed printing mode?

Answer:

If you are using an Epson/Star type printer and you are printing in the normal print mode (secondary addresses 0,1,7 & 8) and you try to send a CHR$(18) which is normally used to turn off the condensed printing mode of your printer you will have a problem. The problem centers around the fact that a Commodore printer doesn't have a condensed print mode and it used CHR$(18) to shift into the reverse printing mode. So if you try to get out of condensed mode you might wind up in reversed printing mode.

There are several solutions that may solve your problem. First, try sending a CHR$(146) instead of the CHR$(18). Second try sending both CHR$(18)CHR$(146) − this combinaton usually works. This last solution always works, open another file to your printer using a secondary address of 4 and send the CHR$(18) out to your printer using that file number.

EXAMPLE:

```
10 OPEN4,4:PRINT#4,"NORMAL "CHR$(20);
20 PRINT#4,"CONDENSED ";:OPEN5,4,4
30 PRINT#5,CHR$(18);:PRINT#4,"NORMAL"
40 CLOSE4:CLOSE5
```

Question:

What do I do if I've tried everything and my interface still doesn't appear to be working?

Answer:

If you have read this manual and tried all of our suggestions and your C/?+G still doesn't seem to be working you have two options.

Your first option is to send us a letter explaining your problem. We answer all of our mail and you should have a response to your question within a week or so.

Your second option is to call our customer service lines at 316-267-6525 and speak to one of our customer service agents about your problem. These lines are often very busy so keep trying.

We want you to be satisfied with your interface and are willing to help you in any way that is possible. If for some reason your interface has to be returned to us, we will try to rush you a new interface within 24 hours of receipt of your defective interface.

Question:

My system is locked up and I don't want to shut everything off and lose all of my data or text, what do I do?

Answer:

Generally not much can be done. The best thing we would recommend would be to totally disconnect the printer interface, then disconnect the disk drive and try to clear the system. Next, reconnect the disk drive then connect the 6 pin connector on the printer interface and last plug in the power

connector to the cassette port. Now if the system is still hung up you should try to clear it again. If these procedures didn't work, give up! Turn off your system and start all over.

Question:

When I try to do a printout from my program, the characters don't seem to line up properly. Why?

Answer:

If you are using a Star Gemini or Epson printer these printers have non-standard sized graphics. Please refer to the section on secondary address #6 for a discussion of the solution to this problem.

C/?+G ASCII Conversion Chart
****

The charts on the following pages will
show you exactly what conversions take place
inside the C/?+G interface. Each optional
secondary address has its own set of
conversion procedures and so each one is
presented as a separate chart. Within most
secondary addresses the QUOTE MODE will
change the conversions in some cases. So
both the QUOTE MODE and normal mode
conversions are listed side by side.

In the following chart the first number
on each line of the conversion table
represents the actual ASCII value of the
character string received by the C/?+G
interface. The second item on each line
represents the character or group of
characters sent to the printer by the C/?+G
interface when the QUOTE MODE function is in
operation. The last item on each line
represents the character (character string
values are shown when non-printable
characters are sent) or FUNCTION sent to the
printer by the C/?+G when operating in the
normal printing mode.

In most cases **one** character (or CHR$
value) received by the interface will
generate **one** character (or CHR$ value) sent
to the printer. There are three exceptions
to this general rule:

1. Character string values (CHR$ values) 1 to
31 and 128 to 159 in the QUOTE MODE are
represented by groups of characters. These

are the SPECIAL LISTING CODES that are described earlier in this manual.

2. In the normal printing mode some cases show a function being performed by the C/?+G instead of a character being sent. In these cases some of the functions are performed internally within the C/?+G interface and no characters are sent to the printer, and in other cases one or more characters may actually be sent. The actual output to the printer from the C/?+G interface for each of these codes may be different for different printer types. You should refer to the section on COMMODORE SPECIAL PRINTER CODES for information on exactly what is sent to accomplish each function for your printer type.

3. In all modes whenever a Commodore graphic character is shown, it is actually sent to the printer as a series of hi-res graphics characters (not simply as one character string value). The sequence of characters required to shift your printer into the graphics mode (refer to the CHR$(8) COMMODORE SPECIAL PRINT COMMAND for an explanation of this function) is sent and then that is followed by the proper graphics character string data required to construct the character as shown. In the following chart these codes will be marked with an "X" following to the right of the character.

NOTE: This chart was printed on a PROWRITER printer. If you are using another type of printer it will produce its own normal character set in the transparent mode, these character sets may be different.

C/?+G ASCII CONVERSION CHART

SECONDARY ADDRESSES 0 (OR NULL) AND 1
NORMAL PRINT MODE UPPER CASE/GRAPHICS

```
CHR$ VALUE      CHR$ VALUE, CHARACTER
RECIEVED        OR FUNCTION SENT
BY THE
C/?+G           QUOTE       NORMAL
INTERFACE       MODE        MODE

CHR$( 0 )       " "         CHR$( 0 )
CHR$( 1 )       "{$1}"      CHR$( 1 )
CHR$( 2 )       "{$2}"      CHR$( 2 )
CHR$( 3 )       "{$3}"      CHR$( 3 )
CHR$( 4 )       "{$4}"      CHR$( 4 )
CHR$( 5 )       "{WHT}"     CHR$( 5 )
CHR$( 6 )       "{$6}"      CHR$( 6 )
CHR$( 7 )       "{$7}"      CHR$( 7 )
CHR$( 8 )       "{DISH}"    START HI-RES GRAPHICS
CHR$( 9 )       "{ENSH}"    CHR$( 9 )
CHR$( 10 )                  CHR$( 10 )
CHR$( 11 )      "{$11}"     CHR$( 11 )
CHR$( 12 )      "{$12}"     CHR$( 12 )
CHR$( 13 )                  CHR$(13) OR
                            CHR$(13) + CHR$(10)
CHR$( 14 )      "{SWLC}"    START EXPANDED PRINT
CHR$( 15 )      "{$15}"     END EXPANDED PRINT
                            OR END GRAPHICS PRINT
CHR$( 16 )      "{$16}"     TAB FUNCTION
CHR$( 17 )      "{C/DN}"    START UPPER/LOWER
                            CASE PRINT MODE
CHR$( 18 )      "{RVON}"    START REVERSED CHARACTERS
CHR$( 19 )      "{HOME}"    CHR$( 19 )
CHR$( 20 )      "{DEL}"     CHR$(20) OR CHR$(15) ON
                            EPSON/STAR PRINTERS
CHR$( 21 )      "{$21}"     CHR$( 21 )
CHR$( 22 )      "{$22}"     CHR$( 22 )
CHR$( 23 )      "{$23}"     CHR$( 23 )
CHR$( 24 )      "{$24}"     CHR$( 24 )
CHR$( 25 )      "{$25}"     CHR$( 25 )
```

C/?+G ASCII CONVERSION CHART (CONT)

SECONDARY ADDRESSES 0 (OR NULL) AND 1
NORMAL PRINT MODE UPPER CASE/GRAPHICS

CHR$ VALUE RECIEVED BY THE C/?+G INTERFACE	CHR$ VALUE, CHARACTER OR FUNCTION SENT	
	QUOTE MODE	NORMAL MODE
CHR$(26)	"{$26}"	CHR$(26) – EXCEPT WHEN IN THE CHR$(8) GRAPHICS MODE THEN IT MEANS REPEAT GRAPHICS CHARACTER
CHR$(27)	"{$27}"	CHR$(27) – UNLESS FOLOWED BY CHR$(16) THEN HI-RES TAB FUNCTION IS SENT
CHR$(28)	"{RED}"	CHR$(28)
CHR$(29)	"{C/RT}"	CHR$(29)
CHR$(30)	"{GRN}"	CHR$(30)
CHR$(31)	"{BLUE}"	CHR$(31)
CHR$(32)	" "	(SPACE)
CHR$(33)	"!"	!
CHR$(34)	"""	"
CHR$(35)	"#"	#
CHR$(36)	"$"	$
CHR$(37)	"%"	%
CHR$(38)	"&"	&
CHR$(39)	"'"	'
CHR$(40)	"("	(
CHR$(41)	")"	)
CHR$(42)	"*"	*
CHR$(43)	"+"	+
CHR$(44)	","	,
CHR$(45)	"-"	-
CHR$(46)	"."	.
CHR$(47)	"/"	/
CHR$(48)	"0"	0
CHR$(49)	"1"	1

C/?+G ASCII CONVERSION CHART (CONT)

SECONDARY ADDRESSES 0 (OR NULL) AND 1
NORMAL PRINT MODE UPPER CASE/GRAPHICS

CHR$ VALUE RECIEVED BY THE C/?+G INTERFACE	CHR$ VALUE, CHARACTER OR FUNCTION SENT	
	QUOTE MODE	NORMAL MODE
CHR$(50)	"2"	2
CHR$(51)	"3"	3
CHR$(52)	"4"	4
CHR$(53)	"5"	5
CHR$(54)	"6"	6
CHR$(55)	"7"	7
CHR$(56)	"8"	8
CHR$(57)	"9"	9
CHR$(58)	":"	:
CHR$(59)	";"	;
CHR$(60)	"<"	<
CHR$(61)	"="	=
CHR$(62)	">"	>
CHR$(63)	"?"	?
CHR$(64)	"ə"	ə
CHR$(65)	"A"	A
CHR$(66)	"B"	B
CHR$(67)	"C"	C
CHR$(68)	"D"	D
CHR$(69)	"E"	E
CHR$(70)	"F"	F
CHR$(71)	"G"	G
CHR$(72)	"H"	H
CHR$(73)	"I"	I
CHR$(74)	"J"	J
CHR$(75)	"K"	K
CHR$(76)	"L"	L
CHR$(77)	"M"	M
CHR$(78)	"N"	N

C/?+G ASCII CONVERSION CHART (CONT)

SECONDARY ADDRESSES 0 (OR NULL) AND 1
NORMAL PRINT MODE UPPER CASE/GRAPHICS

CHR$ VALUE RECIEVED BY THE C/?+G INTERFACE	CHR$ VALUE, CHARACTER OR FUNCTION SENT	
	QUOTE MODE	NORMAL MODE
CHR$(79)	"O"	O
CHR$(80)	"P"	P
CHR$(81)	"Q"	Q
CHR$(82)	"R"	R
CHR$(83)	"S"	S
CHR$(84)	"T"	T
CHR$(85)	"U"	U
CHR$(86)	"V"	V
CHR$(87)	"W"	W
CHR$(88)	"X"	X
CHR$(89)	"Y"	Y
CHR$(90)	"Z"	Z
CHR$(91)	"["	[
CHR$(92)	"£"	£
CHR$(93)	"]"	]
CHR$(94)	"↑"	↑
CHR$(95)	"←"	←
CHR$(96)	"—"	—
CHR$(97)	"♠"	♠
CHR$(98)	"│"	│
CHR$(99)	"—"	—
CHR$(100)	"—"	—
CHR$(101)	"—"	—
CHR$(102)	"_"	_
CHR$(103)	"│"	│
CHR$(104)	"│"	│
CHR$(105)	"╲"	╲
CHR$(106)	"╲"	╲
CHR$(107)	"╱"	╱

C/?+G ASCII CONVERSION CHART (CONT)

SECONDARY ADDRESSES 0 (OR NULL) AND 1
NORMAL PRINT MODE UPPER CASE/GRAPHICS

CHR$ VALUE RECIEVED BY THE C/?+G INTERFACE	CHR$ VALUE, CHARACTER OR FUNCTION SENT QUOTE MODE	NORMAL MODE
CHR$(108)	"L"	L
CHR$(109)	"\"	\
CHR$(110)	"/"	/
CHR$(111)	"Γ"	Γ
CHR$(112)	"˥"	˥
CHR$(113)	"●"	●
CHR$(114)	"_"	_
CHR$(115)	"♥"	♥
CHR$(116)	"│"	│
CHR$(117)	"⌐"	⌐
CHR$(118)	"╳"	╳
CHR$(119)	"○"	○
CHR$(120)	"♠"	♠
CHR$(121)	" │"	│
CHR$(122)	"♦"	♦
CHR$(123)	"+"	+
CHR$(124)	"▓ "	▓
CHR$(125)	"│"	│
CHR$(126)	"π"	π
CHR$(127)	"◤"	◤
CHR$(128)	"{$128}"	CHR$(128)
CHR$(129)	"{ORNG}"	CHR$(129)
CHR$(130)	"{$130}"	CHR$(130)
CHR$(131)	"{$131}"	CHR$(131)
CHR$(132)	"{$132}"	CHR$(132)
CHR$(133)	"{F1}"	CHR$(133)
CHR$(134)	"{F3}"	CHR$(134)
CHR$(135)	"{F5}"	CHR$(135)
CHR$(136)	"{F7}"	CHR$(136)

C/?+G ASCII CONVERSION CHART (CONT)

SECONDARY ADDRESSES 0 (OR NULL) AND 1
NORMAL PRINT MODE UPPER CASE/GRAPHICS

CHR$ VALUE RECIEVED BY THE C/?+G INTERFACE	CHR$ VALUE, CHARACTER OR FUNCTION SENT	
	QUOTE MODE	NORMAL MODE
CHR$(137)	"{F2}"	CHR$(137)
CHR$(138)	"{F4}"	CHR$(138)
CHR$(139)	"{F6}"	CHR$(139)
CHR$(140)	"{F8}"	CHR$(140)
CHR$(141)	"{SHRT}"	CHR$(141)
CHR$(142)	"{SWUC}"	CHR$(142)
CHR$(143)	"{$143}"	CHR$(143)
CHR$(144)	"{BLK}"	CHR$(144)
CHR$(145)	"{C/UP}"	START UPPER CASE/ GRAPHICS MODE
CHR$(146)	"{RVOF}"	END REVERSED CHARACTERS
CHR$(147)	"{CLR}"	CHR$(147)
CHR$(148)	"{INS}"	CHR$(148)
CHR$(149)	"{BRN}"	CHR$(149)
CHR$(150)	"{LRED}"	CHR$(150)
CHR$(151)	"{GRY1}"	CHR$(151)
CHR$(152)	"{GRY2}"	CHR$(152)
CHR$(153)	"{LGRN}"	CHR$(153)
CHR$(154)	"{LBLU}"	CHR$(154)
CHR$(155)	"{GRY3}"	CHR$(155)
CHR$(156)	"{PURP}"	CHR$(156)
CHR$(157)	"{C/LF}"	CHR$(157)
CHR$(158)	"{YELO}"	CHR$(158)
CHR$(159)	"{CYAN}"	CHR$(159)
CHR$(160)	" "	(SPACE)
CHR$(161)	"▌"	▌
CHR$(162)	"▬"	▬
CHR$(163)	"‾"	‾
CHR$(164)	"_"	_
CHR$(165)	"I "	I

C/?+G ASCII CONVERSION CHART (CONT)

SECONDARY ADDRESSES 0 (OR NULL) AND 1
NORMAL PRINT MODE UPPER CASE/GRAPHICS

CHR$ VALUE RECIEVED BY THE C/?+G INTERFACE	CHR$ VALUE, CHARACTER OR FUNCTION SENT	
	QUOTE MODE	NORMAL MODE
CHR$(166)	"▒"	▒
CHR$(167)	" ∣"	∣
CHR$(168)	"ₓₒ"	ₓₒ
CHR$(169)	"◥"	◥
CHR$(170)	" ∣"	∣
CHR$(171)	" ├"	├
CHR$(172)	" ▪"	▪
CHR$(173)	" ∟"	∟
CHR$(174)	"┐ "	┐
CHR$(175)	"▃"	▃
CHR$(176)	" ┌"	┌
CHR$(177)	"⊥"	⊥
CHR$(178)	"┬"	┬
CHR$(179)	"┥"	┥
CHR$(180)	"∣ "	∣
CHR$(181)	"▌ "	▌
CHR$(182)	" ▐"	▐
CHR$(183)	"━"	━
CHR$(184)	"▬"	▬
CHR$(185)	"▃"	▃
CHR$(186)	"⌟"	⌟
CHR$(187)	"▪ "	▪
CHR$(188)	" ▬"	▬
CHR$(189)	"⌐ "	⌐
CHR$(190)	"▪ "	▪
CHR$(191)	"◣"	◣
CHR$(192)	"—"	—
CHR$(193)	"♠"	♠
CHR$(194)	"∣"	∣
CHR$(195)	"—"	—

C/?+G ASCII CONVERSION CHART (CONT)

SECONDARY ADDRESSES 0 (OR NULL) AND 1
NORMAL PRINT MODE UPPER CASE/GRAPHICS

CHR$ VALUE RECIEVED BY THE C/?+G INTERFACE	CHR$ VALUE, CHARACTER OR FUNCTION SENT	
	QUOTE MODE	NORMAL MODE
CHR$(196)	"—"	—
CHR$(197)	"—"	—
CHR$(198)	"_"	_
CHR$(199)	"l"	l
CHR$(200)	" l"	l
CHR$(201)	"\ "	\
CHR$(202)	" \"	\
CHR$(203)	"/ "	/
CHR$(204)	"L"	L
CHR$(205)	"\"	\
CHR$(206)	"/"	/
CHR$(207)	"Γ"	Γ
CHR$(208)	"ᒧ"	ᒧ
CHR$(209)	"●"	●
CHR$(210)	"_"	_
CHR$(211)	"♥"	♥
CHR$(212)	"l "	l
CHR$(213)	" ⌐"	⌐
CHR$(214)	"X"	X
CHR$(215)	"O"	O
CHR$(216)	"♠"	♠
CHR$(217)	" l"	l
CHR$(218)	"♦"	♦
CHR$(219)	"+"	+
CHR$(220)	"§ "	§
CHR$(221)	" l"	l
CHR$(222)	" π"	π
CHR$(223)	"◥"	◥
CHR$(224)	" "	
CHR$(225)	"▌ "	▌

C/?+G ASCII CONVERSION CHART (CONT)

SECONDARY ADDRESSES 0 (OR NULL) AND 1
NORMAL PRINT MODE UPPER CASE/GRAPHICS

CHR$ VALUE   CHR$ VALUE, CHARACTER
RECIEVED   OR FUNCTION SENT
BY THE
C/?+G   QUOTE   NORMAL
INTERFACE   MODE   MODE

CHR$(226)	"▅"	▅
CHR$(227)	"▔"	▔
CHR$(228)	"_"	_
CHR$(229)	"❘ "	❘
CHR$(230)	"▓"	▓
CHR$(231)	" ❘"	❘
CHR$(232)	"⁙"	⁙
CHR$(233)	"◣"	◣
CHR$(234)	" ❙"	❙
CHR$(235)	" ├"	├
CHR$(236)	" ▪"	▪
CHR$(237)	" └"	└
CHR$(238)	"┐ "	┐
CHR$(239)	"▁"	▁
CHR$(240)	" ┌"	┌
CHR$(241)	"⊥"	⊥
CHR$(242)	"┬"	┬
CHR$(243)	"┤ "	┤
CHR$(244)	"❘ "	❘
CHR$(245)	"❙ "	❙
CHR$(246)	" ❙"	❙
CHR$(247)	"▬"	▬
CHR$(248)	"▬"	▬
CHR$(249)	"▬"	▬
CHR$(250)	"┘"	┘
CHR$(251)	"▪ "	▪
CHR$(252)	" ▬"	▬
CHR$(253)	"⌐ "	⌐
CHR$(254)	"▪ "	▪
CHR$(255)	"π"	π

C/?+G ASCII CONVERSION CHART (CONT)

SECONDARY ADDRESSES 3
HEX DUMP MODE

CHR$ VALUE RECIEVED BY THE C/?+G INTERFACE	CHR$ VALUE, CHARACTER OR FUNCTION SENT	
	QUOTE MODE	NORMAL MODE
CHR$(0)	N/A	00
CHR$(1)	N/A	01
CHR$(2)	N/A	02
CHR$(3)	N/A	03
CHR$(4)	N/A	04
CHR$(5)	N/A	05
CHR$(6)	N/A	06
CHR$(7)	N/A	07
CHR$(8)	N/A	08
CHR$(9)	N/A	09
CHR$(10)	N/A	0A
CHR$(11)	N/A	0B
CHR$(12)	N/A	0C
CHR$(13)	N/A	0D
CHR$(14)	N/A	0E
CHR$(15)	N/A	0F
CHR$(16)	N/A	10
CHR$(17)	N/A	11
CHR$(18)	N/A	12
CHR$(19)	N/A	13
CHR$(20)	N/A	14
CHR$(21)	N/A	15
CHR$(22)	N/A	16
CHR$(23)	N/A	17
CHR$(24)	N/A	18
CHR$(25)	N/A	19

C/?+G ASCII CONVERSION CHART (CONT)

SECONDARY ADDRESSES 3
HEX DUMP MODE

CHR$ VALUE RECIEVED BY THE C/?+G INTERFACE	CHR$ VALUE, CHARACTER OR FUNCTION SENT	
	QUOTE MODE	NORMAL MODE
CHR$(26)	N/A	1A
CHR$(27)	N/A	1B
CHR$(28)	N/A	1C
CHR$(29)	N/A	1D
CHR$(30)	N/A	1E
CHR$(31)	N/A	1F
CHR$(32)	N/A	20
CHR$(33)	N/A	21
CHR$(34)	N/A	22
CHR$(35)	N/A	23
CHR$(36)	N/A	24
CHR$(37)	N/A	25
CHR$(38)	N/A	26
CHR$(39)	N/A	27
CHR$(40)	N/A	28
CHR$(41)	N/A	29
CHR$(42)	N/A	2A
CHR$(43)	N/A	2B
CHR$(44)	N/A	2C
CHR$(45)	N/A	2D
CHR$(46)	N/A	2E
CHR$(47)	N/A	2F
CHR$(48)	N/A	30
CHR$(49)	N/A	31
CHR$(50)	N/A	32
CHR$(51)	N/A	33
CHR$(52)	N/A	34

C/?+G ASCII CONVERSION CHART (CONT)

SECONDARY ADDRESSES 3
HEX DUMP MODE

CHR$ VALUE RECIEVED BY THE C/?+G INTERFACE	CHR$ VALUE, CHARACTER OR FUNCTION SENT	
	QUOTE MODE	NORMAL MODE
CHR$(53)	N/A	35
CHR$(54)	N/A	36
CHR$(55)	N/A	37
CHR$(56)	N/A	38
CHR$(57)	N/A	39
CHR$(58)	N/A	3A
CHR$(59)	N/A	3B
CHR$(60)	N/A	3C
CHR$(61)	N/A	3D
CHR$(62)	N/A	3E
CHR$(63)	N/A	3F
CHR$(64)	N/A	40
CHR$(65)	N/A	41
CHR$(66)	N/A	42
CHR$(67)	N/A	43
CHR$(68)	N/A	44
CHR$(69)	N/A	45
CHR$(70)	N/A	46
CHR$(71)	N/A	47
CHR$(72)	N/A	48
CHR$(73)	N/A	49
CHR$(74)	N/A	4A
CHR$(75)	N/A	4B
CHR$(76)	N/A	4C
CHR$(77)	N/A	4D
CHR$(78)	N/A	4E
CHR$(79)	N/A	4F
CHR$(80)	N/A	50
CHR$(81)	N/A	51

C/?+G ASCII CONVERSION CHART (CONT)

SECONDARY ADDRESSES 3
HEX DUMP MODE

CHR$ VALUE RECIEVED BY THE C/?+G INTERFACE	CHR$ VALUE, CHARACTER OR FUNCTION SENT	
	QUOTE MODE	NORMAL MODE
CHR$(82)	N/A	52
CHR$(83)	N/A	53
CHR$(84)	N/A	54
CHR$(85)	N/A	55
CHR$(86)	N/A	56
CHR$(87)	N/A	57
CHR$(88)	N/A	58
CHR$(89)	N/A	59
CHR$(90)	N/A	5A
CHR$(91)	N/A	5B
CHR$(92)	N/A	5C
CHR$(93)	N/A	5D
CHR$(94)	N/A	5E
CHR$(95)	N/A	5F
CHR$(96)	N/A	60
CHR$(97)	N/A	61
CHR$(98)	N/A	62
CHR$(99)	N/A	63
CHR$(100)	N/A	64
CHR$(101)	N/A	65
CHR$(102)	N/A	66
CHR$(103)	N/A	67
CHR$(104)	N/A	68
CHR$(105)	N/A	69
CHR$(106)	N/A	6A
CHR$(107)	N/A	6B
CHR$(108)	N/A	6C
CHR$(109)	N/A	6D
CHR$(110)	N/A	6E

C/?+G ASCII CONVERSION CHART (CONT)

SECONDARY ADDRESSES 3
HEX DUMP MODE

CHR$ VALUE RECIEVED BY THE C/?+G INTERFACE	CHR$ VALUE, CHARACTER OR FUNCTION SENT QUOTE MODE	NORMAL MODE
CHR$(111)	N/A	6F
CHR$(112)	N/A	70
CHR$(113)	N/A	71
CHR$(114)	N/A	72
CHR$(115)	N/A	73
CHR$(116)	N/A	74
CHR$(117)	N/A	75
CHR$(118)	N/A	76
CHR$(119)	N/A	77
CHR$(120)	N/A	78
CHR$(121)	N/A	79
CHR$(122)	N/A	7A
CHR$(123)	N/A	7B
CHR$(124)	N/A	7C
CHR$(125)	N/A	7D
CHR$(126)	N/A	7E
CHR$(127)	N/A	7F
CHR$(128)	N/A	80
CHR$(129)	N/A	81
CHR$(130)	N/A	82
CHR$(131)	N/A	83
CHR$(132)	N/A	84
CHR$(133)	N/A	85
CHR$(134)	N/A	86
CHR$(135)	N/A	87
CHR$(136)	N/A	88
CHR$(137)	N/A	89
CHR$(138)	N/A	8A
CHR$(139)	N/A	8B

C/?+G ASCII CONVERSION CHART (CONT)

SECONDARY ADDRESSES 3
HEX DUMP MODE

CHR$ VALUE RECIEVED BY THE C/?+G INTERFACE	CHR$ VALUE, CHARACTER OR FUNCTION SENT	
	QUOTE MODE	NORMAL MODE
CHR$(140)	N/A	8C
CHR$(141)	N/A	8D
CHR$(142)	N/A	8E
CHR$(143)	N/A	8F
CHR$(144)	N/A	90
CHR$(145)	N/A	91
CHR$(146)	N/A	92
CHR$(147)	N/A	93
CHR$(148)	N/A	94
CHR$(149)	N/A	95
CHR$(150)	N/A	96
CHR$(151)	N/A	97
CHR$(152)	N/A	98
CHR$(153)	N/A	99
CHR$(154)	N/A	9A
CHR$(155)	N/A	9B
CHR$(156)	N/A	9C
CHR$(157)	N/A	9D
CHR$(158)	N/A	9E
CHR$(159)	N/A	9F
CHR$(160)	N/A	A0
CHR$(161)	N/A	A1
CHR$(162)	N/A	A2
CHR$(163)	N/A	A3
CHR$(164)	N/A	A4
CHR$(165)	N/A	A5
CHR$(166)	N/A	A6
CHR$(167)	N/A	A7

C/?+G ASCII CONVERSION CHART (CONT)

SECONDARY ADDRESSES 3
HEX DUMP MODE

CHR$ VALUE RECIEVED BY THE C/?+G INTERFACE	CHR$ VALUE, CHARACTER OR FUNCTION SENT	
	QUOTE MODE	NORMAL MODE
CHR$(168)	N/A	A8
CHR$(169)	N/A	A9
CHR$(170)	N/A	AA
CHR$(171)	N/A	AB
CHR$(172)	N/A	AC
CHR$(173)	N/A	AD
CHR$(174)	N/A	AE
CHR$(175)	N/A	AF
CHR$(176)	N/A	B0
CHR$(177)	N/A	B1
CHR$(178)	N/A	B2
CHR$(179)	N/A	B3
CHR$(180)	N/A	B4
CHR$(181)	N/A	B5
CHR$(182)	N/A	B6
CHR$(183)	N/A	B7
CHR$(184)	N/A	B8
CHR$(185)	N/A	B9
CHR$(186)	N/A	BA
CHR$(187)	N/A	BB
CHR$(188)	N/A	BC
CHR$(189)	N/A	BD
CHR$(190)	N/A	BE
CHR$(191)	N/A	BF
CHR$(192)	N/A	C0
CHR$(193)	N/A	C1
CHR$(194)	N/A	C2
CHR$(195)	N/A	C3
CHR$(196)	N/A	C4

C/?+G ASCII CONVERSION CHART (CONT)

SECONDARY ADDRESSES 3
HEX DUMP MODE

CHR$ VALUE RECIEVED BY THE C/?+G INTERFACE	CHR$ VALUE, CHARACTER OR FUNCTION SENT	
	QUOTE MODE	NORMAL MODE
CHR$(197)	N/A	C5
CHR$(198)	N/A	C6
CHR$(199)	N/A	C7
CHR$(200)	N/A	C8
CHR$(201)	N/A	C9
CHR$(202)	N/A	CA
CHR$(203)	N/A	CB
CHR$(204)	N/A	CC
CHR$(205)	N/A	CD
CHR$(206)	N/A	CE
CHR$(207)	N/A	CF
CHR$(208)	N/A	D0
CHR$(209)	N/A	D1
CHR$(210)	N/A	D2
CHR$(211)	N/A	D3
CHR$(212)	N/A	D4
CHR$(213)	N/A	D5
CHR$(214)	N/A	D6
CHR$(215)	N/A	D7
CHR$(216)	N/A	D8
CHR$(217)	N/A	D9
CHR$(218)	N/A	DA
CHR$(219)	N/A	DB
CHR$(220)	N/A	DC
CHR$(221)	N/A	DD
CHR$(222)	N/A	DE
CHR$(223)	N/A	DF
CHR$(224)	N/A	E0
CHR$(225)	N/A	E1

C/?+G ASCII CONVERSION CHART (CONT)

SECONDARY ADDRESSES 3
HEX DUMP MODE

CHR$ VALUE RECIEVED BY THE C/?+G INTERFACE	CHR$ VALUE, CHARACTER OR FUNCTION SENT	
	QUOTE MODE	NORMAL MODE
CHR$(226)	N/A	E2
CHR$(227)	N/A	E3
CHR$(228)	N/A	E4
CHR$(229)	N/A	E5
CHR$(230)	N/A	E6
CHR$(231)	N/A	E7
CHR$(232)	N/A	E8
CHR$(233)	N/A	E9
CHR$(234)	N/A	EA
CHR$(235)	N/A	EB
CHR$(236)	N/A	EC
CHR$(237)	N/A	ED
CHR$(238)	N/A	EE
CHR$(239)	N/A	EF
CHR$(240)	N/A	F0
CHR$(241)	N/A	F1
CHR$(242)	N/A	F2
CHR$(243)	N/A	F3
CHR$(244)	N/A	F4
CHR$(245)	N/A	F5
CHR$(246)	N/A	F6
CHR$(247)	N/A	F7
CHR$(248)	N/A	F8
CHR$(249)	N/A	F9
CHR$(250)	N/A	FA
CHR$(251)	N/A	FB
CHR$(252)	N/A	FC
CHR$(253)	N/A	FD
CHR$(254)	N/A	FE
CHR$(255)	N/A	FF

C/?+G ASCII CONVERSION CHART (CONT)

SECONDARY ADDRESSES 4 OR 5
TRANSPARENT MODE

CHR$ VALUE RECIEVED BY THE C/?+G INTERFACE	CHR$ VALUE, CHARACTER OR FUNCTION SENT	
	QUOTE MODE	NORMAL MODE
CHR$(0)	N/A	CHR$(0)
CHR$(1)	N/A	CHR$(1)
CHR$(2)	N/A	CHR$(2)
CHR$(3)	N/A	CHR$(3)
CHR$(4)	N/A	CHR$(4)
CHR$(5)	N/A	CHR$(5)
CHR$(6)	N/A	CHR$(6)
CHR$(7)	N/A	CHR$(7)
CHR$(8)	N/A	CHR$(8)
CHR$(9)	N/A	CHR$(9)
CHR$(10)	N/A	CHR$(10)
CHR$(11)	N/A	CHR$(11)
CHR$(12)	N/A	CHR$(12)
CHR$(13)	N/A	CHR$(13)
CHR$(14)	N/A	CHR$(14)
CHR$(15)	N/A	CHR$(15)
CHR$(16)	N/A	CHR$(16)
CHR$(17)	N/A	CHR$(17)
CHR$(18)	N/A	CHR$(18)
CHR$(19)	N/A	CHR$(19)
CHR$(20)	N/A	CHR$(20)
CHR$(21)	N/A	CHR$(21)
CHR$(22)	N/A	CHR$(22)
CHR$(23)	N/A	CHR$(23)
CHR$(24)	N/A	CHR$(24)
CHR$(25)	N/A	CHR$(25)

C/?+G ASCII CONVERSION CHART (CONT)

SECONDARY ADDRESSES 4 OR 5
TRANSPARENT MODE

CHR$ VALUE RECIEVED BY THE C/?+G INTERFACE	CHR$ VALUE, CHARACTER OR FUNCTION SENT	
	QUOTE MODE	NORMAL MODE
CHR$(26)	N/A	CHR$(26)
CHR$(27)	N/A	CHR$(27)
CHR$(28)	N/A	CHR$(28)
CHR$(29)	N/A	CHR$(29)
CHR$(30)	N/A	CHR$(30)
CHR$(31)	N/A	CHR$(31)
CHR$(32)	N/A	(SPACE)
CHR$(33)	N/A	!
CHR$(34)	N/A	"
CHR$(35)	N/A	#
CHR$(36)	N/A	$
CHR$(37)	N/A	%
CHR$(38)	N/A	&
CHR$(39)	N/A	'
CHR$(40)	N/A	(
CHR$(41)	N/A	)
CHR$(42)	N/A	*
CHR$(43)	N/A	+
CHR$(44)	N/A	,
CHR$(45)	N/A	–
CHR$(46)	N/A	.
CHR$(47)	N/A	/
CHR$(48)	N/A	0
CHR$(49)	N/A	1
CHR$(50)	N/A	2
CHR$(51)	N/A	3
CHR$(52)	N/A	4

C/?+G ASCII CONVERSION CHART (CONT)

SECONDARY ADDRESSES 4 OR 5
TRANSPARENT MODE

CHR$ VALUE RECIEVED BY THE C/?+G INTERFACE	CHR$ VALUE, CHARACTER OR FUNCTION SENT	
	QUOTE MODE	NORMAL MODE
CHR$(53)	N/A	5
CHR$(54)	N/A	6
CHR$(55)	N/A	7
CHR$(56)	N/A	8
CHR$(57)	N/A	9
CHR$(58)	N/A	:
CHR$(59)	N/A	;
CHR$(60)	N/A	<
CHR$(61)	N/A	=
CHR$(62)	N/A	>
CHR$(63)	N/A	?
CHR$(64)	N/A	@
CHR$(65)	N/A	A
CHR$(66)	N/A	B
CHR$(67)	N/A	C
CHR$(68)	N/A	D
CHR$(69)	N/A	E
CHR$(70)	N/A	F
CHR$(71)	N/A	G
CHR$(72)	N/A	H
CHR$(73)	N/A	I
CHR$(74)	N/A	J
CHR$(75)	N/A	K
CHR$(76)	N/A	L
CHR$(77)	N/A	M
CHR$(78)	N/A	N
CHR$(79)	N/A	O
CHR$(80)	N/A	P
CHR$(81)	N/A	Q

C/?+G ASCII CONVERSION CHART (CONT)

SECONDARY ADDRESSES 4 OR 5
TRANSPARENT MODE

CHR$ VALUE RECIEVED BY THE C/?+G INTERFACE	CHR$ VALUE, CHARACTER OR FUNCTION SENT	
	QUOTE MODE	NORMAL MODE
CHR$(82)	N/A	R
CHR$(83)	N/A	S
CHR$(84)	N/A	T
CHR$(85)	N/A	U
CHR$(86)	N/A	V
CHR$(87)	N/A	W
CHR$(88)	N/A	X
CHR$(89)	N/A	Y
CHR$(90)	N/A	Z
CHR$(91)	N/A	[
CHR$(92)	N/A	\
CHR$(93)	N/A	]
CHR$(94)	N/A	^
CHR$(95)	N/A	_
CHR$(96)	N/A	`
CHR$(97)	N/A	a
CHR$(98)	N/A	b
CHR$(99)	N/A	c
CHR$(100)	N/A	d
CHR$(101)	N/A	e
CHR$(102)	N/A	f
CHR$(103)	N/A	g
CHR$(104)	N/A	h
CHR$(105)	N/A	i
CHR$(106)	N/A	j
CHR$(107)	N/A	k
CHR$(108)	N/A	l
CHR$(109)	N/A	m
CHR$(110)	N/A	n

C/?+G ASCII CONVERSION CHART (CONT)

SECONDARY ADDRESSES 4 OR 5
TRANSPARENT MODE

CHR$ VALUE RECIEVED BY THE C/?+G INTERFACE	CHR$ VALUE, CHARACTER OR FUNCTION SENT	
	QUOTE MODE	NORMAL MODE
CHR$(111)	N/A	o
CHR$(112)	N/A	p
CHR$(113)	N/A	q
CHR$(114)	N/A	r
CHR$(115)	N/A	s
CHR$(116)	N/A	t
CHR$(117)	N/A	u
CHR$(118)	N/A	v
CHR$(119)	N/A	w
CHR$(120)	N/A	x
CHR$(121)	N/A	y
CHR$(122)	N/A	z
CHR$(123)	N/A	{
CHR$(124)	N/A	!
CHR$(125)	N/A	}
CHR$(126)	N/A	~
CHR$(127)	N/A	
CHR$(128)	N/A	CHR$(128)
CHR$(129)	N/A	CHR$(129)
CHR$(130)	N/A	CHR$(130)
CHR$(131)	N/A	CHR$(131)
CHR$(132)	N/A	CHR$(132)
CHR$(133)	N/A	CHR$(133)
CHR$(134)	N/A	CHR$(134)
CHR$(135)	N/A	CHR$(135)
CHR$(136)	N/A	CHR$(136)
CHR$(137)	N/A	CHR$(137)
CHR$(138)	N/A	CHR$(138)
CHR$(139)	N/A	CHR$(139)

C/?+G ASCII CONVERSION CHART (CONT)

SECONDARY ADDRESSES 4 OR 5
TRANSPARENT MODE

CHR$ VALUE RECIEVED BY THE C/?+G INTERFACE	CHR$ VALUE, CHARACTER OR FUNCTION SENT	
	QUOTE MODE	NORMAL MODE
CHR$(140)	N/A	CHR$(140)
CHR$(141)	N/A	CHR$(141)
CHR$(142)	N/A	CHR$(142)
CHR$(143)	N/A	CHR$(143)
CHR$(144)	N/A	CHR$(144)
CHR$(145)	N/A	CHR$(145)
CHR$(146)	N/A	CHR$(146)
CHR$(147)	N/A	CHR$(147)
CHR$(148)	N/A	CHR$(148)
CHR$(149)	N/A	CHR$(149)
CHR$(150)	N/A	CHR$(150)
CHR$(151)	N/A	CHR$(151)
CHR$(152)	N/A	CHR$(152)
CHR$(153)	N/A	CHR$(153)
CHR$(154)	N/A	CHR$(154)
CHR$(155)	N/A	CHR$(155)
CHR$(156)	N/A	CHR$(156)
CHR$(157)	N/A	CHR$(157)
CHR$(158)	N/A	CHR$(158)
CHR$(159)	N/A	CHR$(159)
CHR$(160)	N/A	(SPACE)
CHR$(161)	N/A	°
CHR$(162)	N/A	┌
CHR$(163)	N/A	┘
CHR$(164)	N/A	＼
CHR$(165)	N/A	・
CHR$(166)	N/A	ヲ
CHR$(167)	N/A	ァ

C/?+G ASCII CONVERSION CHART (CONT)

SECONDARY ADDRESSES 4 OR 5
TRANSPARENT MODE

CHR$ VALUE RECIEVED BY THE C/?+G INTERFACE	CHR$ VALUE, CHARACTER OR FUNCTION SENT	
	QUOTE MODE	NORMAL MODE
CHR$(168)	N/A	ィ
CHR$(169)	N/A	ゥ
CHR$(170)	N/A	ェ
CHR$(171)	N/A	ォ
CHR$(172)	N/A	ャ
CHR$(173)	N/A	ュ
CHR$(174)	N/A	ョ
CHR$(175)	N/A	ッ
CHR$(176)	N/A	ー
CHR$(177)	N/A	ア
CHR$(178)	N/A	イ
CHR$(179)	N/A	ウ
CHR$(180)	N/A	エ
CHR$(181)	N/A	オ
CHR$(182)	N/A	カ
CHR$(183)	N/A	キ
CHR$(184)	N/A	ク
CHR$(185)	N/A	ケ
CHR$(186)	N/A	コ
CHR$(187)	N/A	サ
CHR$(188)	N/A	シ
CHR$(189)	N/A	ス
CHR$(190)	N/A	セ
CHR$(191)	N/A	ソ
CHR$(192)	N/A	タ
CHR$(193)	N/A	チ
CHR$(194)	N/A	ツ
CHR$(195)	N/A	テ
CHR$(196)	N/A	ト

C/?+G ASCII CONVERSION CHART (CONT)

SECONDARY ADDRESSES 4 OR 5
TRANSPARENT MODE

CHR$ VALUE RECIEVED BY THE C/?+G INTERFACE	CHR$ VALUE, CHARACTER OR FUNCTION SENT	
	QUOTE MODE	NORMAL MODE
CHR$(197)	N/A	ナ
CHR$(198)	N/A	ニ
CHR$(199)	N/A	ヌ
CHR$(200)	N/A	ネ
CHR$(201)	N/A	ノ
CHR$(202)	N/A	ハ
CHR$(203)	N/A	ヒ
CHR$(204)	N/A	フ
CHR$(205)	N/A	ヘ
CHR$(206)	N/A	ホ
CHR$(207)	N/A	マ
CHR$(208)	N/A	ミ
CHR$(209)	N/A	ム
CHR$(210)	N/A	メ
CHR$(211)	N/A	モ
CHR$(212)	N/A	ヤ
CHR$(213)	N/A	ユ
CHR$(214)	N/A	ヨ
CHR$(215)	N/A	ラ
CHR$(216)	N/A	リ
CHR$(217)	N/A	ル
CHR$(218)	N/A	レ
CHR$(219)	N/A	ロ
CHR$(220)	N/A	ワ
CHR$(221)	N/A	ン
CHR$(222)	N/A	゛
CHR$(223)	N/A	゜
CHR$(224)	N/A	=
CHR$(225)	N/A	ト

C/?+G ASCII CONVERSION CHART (CONT)

SECONDARY ADDRESSES 4 OR 5
TRANSPARENT MODE

CHR$ VALUE RECIEVED BY THE C/?+G INTERFACE	CHR$ VALUE, CHARACTER OR FUNCTION SENT	
	QUOTE MODE	NORMAL MODE
CHR$(226)	N/A	‡
CHR$(227)	N/A	⊣
CHR$(228)	N/A	◢
CHR$(229)	N/A	◣
CHR$(230)	N/A	◥
CHR$(231)	N/A	◤
CHR$(232)	N/A	♠
CHR$(233)	N/A	♥
CHR$(234)	N/A	♦
CHR$(235)	N/A	♣
CHR$(236)	N/A	●
CHR$(237)	N/A	o
CHR$(238)	N/A	/
CHR$(239)	N/A	\
CHR$(240)	N/A	X
CHR$(241)	N/A	⋯
CHR$(242)	N/A	⋮
CHR$(243)	N/A	⊥
CHR$(244)	N/A	⊤
CHR$(245)	N/A	⊣
CHR$(246)	N/A	⊢
CHR$(247)	N/A	⊹
CHR$(248)	N/A	
CHR$(249)	N/A	
CHR$(250)	N/A	
CHR$(251)	N/A	
CHR$(252)	N/A	
CHR$(253)	N/A	
CHR$(254)	N/A	
CHR$(255)	N/A	

C/?+G ASCII CONVERSION CHART (CONT)

SECONDARY ADDRESSES 6
CHARACTER PRINT MODE

CHR$ VALUE RECIEVED BY THE C/?+G INTERFACE	CHR$ VALUE, CHARACTER OR FUNCTION SENT	
	QUOTE MODE	NORMAL MODE
CHR$(0)	" "	CHR$(0)
CHR$(1)	"{$1}"	CHR$(1)
CHR$(2)	"{$2}"	CHR$(2)
CHR$(3)	"{$3}"	CHR$(3)
CHR$(4)	"{$4}"	CHR$(4)
CHR$(5)	"{WHT}"	CHR$(5)
CHR$(6)	"{$6}"	CHR$(6)
CHR$(7)	"{$7}"	CHR$(7)
CHR$(8)	"{DISH}"	START HI-RES GRAPHICS
CHR$(9)	"{ENSH}"	CHR$(9)
CHR$(10)		CHR$(10)
CHR$(11)	"{$11}"	CHR$(11)
CHR$(12)	"{$12}"	CHR$(12)
CHR$(13)	`	CHR$(13) OR CHR$(13) + CHR$(10)
CHR$(14)	"{SWLC}"	START EXPANDED PRINT
CHR$(15)	"{$15}"	END EXPANDED PRINT OR END GRAPHICS PRINT
CHR$(16)	"{$16}"	TAB FUNCTION
CHR$(17)	"{C/DN}"	START UPPER/LOWER CASE PRINT MODE
CHR$(18)	"{RVON}"	START REVERSED CHARACTERS
CHR$(19)	"{HOME}"	CHR$(19)
CHR$(20)	"{DEL}"	CHR$(20) OR CHR$(15) ON EPSON/STAR PRINTERS
CHR$(21)	"{$21}"	CHR$(21)
CHR$(22)	"{$22}"	CHR$(22)
CHR$(23)	"{$23}"	CHR$(23)
CHR$(24)	"{$24}"	CHR$(24)
CHR$(25)	"{$25}"	CHR$(25)

C/?+G ASCII CONVERSION CHART (CONT)

SECONDARY ADDRESSES 6
CHARACTER PRINT MODE

CHR$ VALUE RECIEVED BY THE C/?+G INTERFACE	CHR$ VALUE, CHARACTER OR FUNCTION SENT	
	QUOTE MODE	NORMAL MODE
CHR$(26)	"{$26}"	CHR$(26) - EXCEPT WHEN IN THE CHR$(8) GRAPHICS THEN IT MEANS REPEAT GRAPHICS CHARACTER
CHR$(27)	"{$27}"	CHR$(27) - UNLESS FOLOWED BY CHR$(16) THEN HI-RES TAB FUNCTION IS SENT
CHR$(28)	"{RED}"	CHR$(28)
CHR$(29)	"{C/RT}"	CHR$(29)
CHR$(30)	"{GRN}"	CHR$(30)
CHR$(31)	"{BLUE}"	CHR$(31)
CHR$(32)	" "	(SPACE)
CHR$(33)	"!"	!
CHR$(34)	"""	"
CHR$(35)	"#"	#
CHR$(36)	"$"	$
CHR$(37)	"%"	%
CHR$(38)	"&"	&
CHR$(39)	"'"	'
CHR$(40)	"("	(
CHR$(41)	")"	)
CHR$(42)	"*"	*
CHR$(43)	"+"	+
CHR$(44)	","	,
CHR$(45)	"-"	-
CHR$(46)	"."	.
CHR$(47)	"/"	/
CHR$(48)	"0"	0
CHR$(49)	"1"	1

C/?+G ASCII CONVERSION CHART (CONT)

SECONDARY ADDRESSES 6
CHARACTER PRINT MODE

CHR$ VALUE RECIEVED BY THE C/?+G INTERFACE	CHR$ VALUE, CHARACTER OR FUNCTION SENT	
	QUOTE MODE	NORMAL MODE
CHR$(50)	"2"	2
CHR$(51)	"3"	3
CHR$(52)	"4"	4
CHR$(53)	"5"	5
CHR$(54)	"6"	6
CHR$(55)	"7"	7
CHR$(56)	"8"	8
CHR$(57)	"9"	9
CHR$(58)	":"	:
CHR$(59)	";"	;
CHR$(60)	"<"	<
CHR$(61)	"="	=
CHR$(62)	">"	>
CHR$(63)	"?"	?
CHR$(64)	"@"	@
CHR$(65)	"a"	a
CHR$(66)	"b"	b
CHR$(67)	"c"	c
CHR$(68)	"d"	d
CHR$(69)	"e"	e
CHR$(70)	"f"	f
CHR$(71)	"g"	g
CHR$(72)	"h"	h
CHR$(73)	"i"	i
CHR$(74)	"j"	j
CHR$(75)	"k"	k
CHR$(76)	"l"	l
CHR$(77)	"m"	m
CHR$(78)	"n"	n

C/?+G ASCII CONVERSION CHART (CONT)

SECONDARY ADDRESSES 6
CHARACTER PRINT MODE

CHR$ VALUE RECIEVED BY THE C/?+G INTERFACE	CHR$ VALUE, CHARACTER OR FUNCTION SENT	
	QUOTE MODE	NORMAL MODE
CHR$(79)	"o"	o
CHR$(80)	"p"	p
CHR$(81)	"q"	q
CHR$(82)	"r"	r
CHR$(83)	"s"	s
CHR$(84)	"t"	t
CHR$(85)	"u"	u
CHR$(86)	"v"	v
CHR$(87)	"w"	w
CHR$(88)	"x"	x
CHR$(89)	"y"	y
CHR$(90)	"z"	z
CHR$(91)	"["	[
CHR$(92)	"£"	£
CHR$(93)	"]"	]
CHR$(94)	"↑"	↑
CHR$(95)	"←"	←
CHR$(96)	"—"	—
CHR$(97)	"A"	A
CHR$(98)	"B"	B
CHR$(99)	"C"	C
CHR$(100)	"D"	D
CHR$(101)	"E"	E
CHR$(102)	"F"	F
CHR$(103)	"G"	G
CHR$(104)	"H"	H
CHR$(105)	"I"	I
CHR$(106)	"J"	J
CHR$(107)	"K"	K

C/?+G ASCII CONVERSION CHART (CONT)

SECONDARY ADDRESSES 6
CHARACTER PRINT MODE

CHR$ VALUE RECIEVED BY THE C/?+G INTERFACE	CHR$ VALUE, CHARACTER OR FUNCTION SENT	
	QUOTE MODE	NORMAL MODE
CHR$(108)	"L"	L
CHR$(109)	"M"	M
CHR$(110)	"N"	N
CHR$(111)	"O"	O
CHR$(112)	"P"	P
CHR$(113)	"Q"	Q
CHR$(114)	"R"	R
CHR$(115)	"S"	S
CHR$(116)	"T"	T
CHR$(117)	"U"	U
CHR$(118)	"V"	V
CHR$(119)	"W"	W
CHR$(120)	"X"	X
CHR$(121)	"Y"	Y
CHR$(122)	"Z"	Z
CHR$(123)	"+"	+
CHR$(124)	"▓ "	▓
CHR$(125)	"	"		
CHR$(126)	"▨"	▨
CHR$(127)	"▨"	▨
CHR$(128)	"($128)"	CHR$(128)
CHR$(129)	"(ORNG)"	CHR$(129)
CHR$(130)	"($130)"	CHR$(130)
CHR$(131)	"($131)"	CHR$(131)
CHR$(132)	"($132)"	CHR$(132)
CHR$(133)	"(F1)"	CHR$(133)
CHR$(134)	"(F3)"	CHR$(134)
CHR$(135)	"(F5)"	CHR$(135)
CHR$(136)	"(F7)"	CHR$(136)

C/?+G ASCII CONVERSION CHART (CONT)

SECONDARY ADDRESSES 6
CHARACTER PRINT MODE

CHR$ VALUE RECIEVED BY THE C/?+G INTERFACE	CHR$ VALUE, CHARACTER OR FUNCTION SENT	
	QUOTE MODE	NORMAL MODE
CHR$(137)	"{F2}"	CHR$(137)
CHR$(138)	"{F4}"	CHR$(138)
CHR$(139)	"{F6}"	CHR$(139)
CHR$(140)	"{F8}"	CHR$(140)
CHR$(141)	"{SHRT}"	CHR$(141)
CHR$(142)	"{SWUC}"	CHR$(142)
CHR$(143)	"{$143}"	CHR$(143)
CHR$(144)	"{BLK}"	CHR$(144)
CHR$(145)	"{C/UP}"	START UPPER CASE/ GRAPHICS MODE
CHR$(146)	"{RVOF}"	END REVERSED CHARACTERS
CHR$(147)	"{CLR}"	CHR$(147)
CHR$(148)	"{INS}"	CHR$(148)
CHR$(149)	"{BRN}"	CHR$(149)
CHR$(150)	"{LRED}"	CHR$(150)
CHR$(151)	"{GRY1}"	CHR$(151)
CHR$(152)	"{GRY2}"	CHR$(152)
CHR$(153)	"{LGRN}"	CHR$(153)
CHR$(154)	"{LBLU}"	CHR$(154)
CHR$(155)	"{GRY3}"	CHR$(155)
CHR$(156)	"{PURP}"	CHR$(156)
CHR$(157)	"{C/LF}"	CHR$(157)
CHR$(158)	"{YELO}"	CHR$(158)
CHR$(159)	"{CYAN}"	CHR$(159)
CHR$(160)	" "	(SPACE)
CHR$(161)	"▌"	▌
CHR$(162)	"▄"	▄
CHR$(163)	"‾"	‾
CHR$(164)	"_"	_
CHR$(165)	"│"	│

C/?+G ASCII CONVERSION CHART (CONT)

SECONDARY ADDRESSES 6
CHARACTER PRINT MODE

CHR$ VALUE RECIEVED BY THE C/?+G INTERFACE	CHR$ VALUE, CHARACTER OR FUNCTION SENT	
	QUOTE MODE	NORMAL MODE
CHR$(166)	"▓"	▓
CHR$(167)	" ⌐"	⌐
CHR$(168)	"⁙"	⁙
CHR$(169)	"▓"	▓
CHR$(170)	" ▌"	▌
CHR$(171)	" ├"	├
CHR$(172)	" ▪"	▪
CHR$(173)	" ∟"	∟
CHR$(174)	"¬ "	¬
CHR$(175)	"_"	_
CHR$(176)	" ┌"	┌
CHR$(177)	"⊥"	⊥
CHR$(178)	"┬"	┬
CHR$(179)	"┤ "	┤
CHR$(180)	"▌ "	▌
CHR$(181)	"▌ "	▌
CHR$(182)	" ▐"	▐
CHR$(183)	"▬"	▬
CHR$(184)	"▬"	▬
CHR$(185)	"▄"	▄
CHR$(186)	"∕"	∕
CHR$(187)	"▪ "	▪
CHR$(188)	" ▬"	▬
CHR$(189)	"⌐ "	⌐
CHR$(190)	"▪ "	▪
CHR$(191)	"▚"	▚
CHR$(192)	"_"	_
CHR$(193)	"A"	A
CHR$(194)	"B"	B
CHR$(195)	"C"	C

C/?+G ASCII CONVERSION CHART (CONT)

SECONDARY ADDRESSES 6
CHARACTER PRINT MODE

CHR$ VALUE RECIEVED BY THE C/?+G INTERFACE	CHR$ VALUE, CHARACTER OR FUNCTION SENT	
	QUOTE MODE	NORMAL MODE
CHR$(196)	"D"	D
CHR$(197)	"E"	E
CHR$(198)	"F"	F
CHR$(199)	"G"	G
CHR$(200)	"H"	H
CHR$(201)	"I"	I
CHR$(202)	"J"	J
CHR$(203)	"K"	K
CHR$(204)	"L"	L
CHR$(205)	"M"	M
CHR$(206)	"N"	N
CHR$(207)	"O"	O
CHR$(208)	"P"	P
CHR$(209)	"Q"	Q
CHR$(210)	"R"	R
CHR$(211)	"S"	S
CHR$(212)	"T"	T
CHR$(213)	"U"	U
CHR$(214)	"V"	V
CHR$(215)	"W"	W
CHR$(216)	"X"	X
CHR$(217)	"Y"	Y
CHR$(218)	"Z"	Z
CHR$(219)	"+"	+
CHR$(220)	"▓ "	▓
CHR$(221)	" I "	I
CHR$(222)	"✗"	✗
CHR$(223)	"▓▓"	▓▓
CHR$(224)	" "	
CHR$(225)	"▮ "	▮

C/?+G ASCII CONVERSION CHART (CONT)

SECONDARY ADDRESSES 6
CHARACTER PRINT MODE

CHR$ VALUE RECIEVED BY THE C/?+G INTERFACE	CHR$ VALUE, CHARACTER OR FUNCTION SENT	
	QUOTE MODE	NORMAL MODE ·
CHR$(226)	"■"	■
CHR$(227)	"─"	─
CHR$(228)	"_"	_
CHR$(229)	"│ "	│
CHR$(230)	"▩"	▩
CHR$(231)	" │"	│
CHR$(232)	"⋌"	⋌
CHR$(233)	"▩"	▩
CHR$(234)	" │"	│
CHR$(235)	" ├"	├
CHR$(236)	" ■"	■
CHR$(237)	" └"	└
CHR$(238)	"┐ "	┐
CHR$(239)	"_"	─
CHR$(240)	" ┌"	┌
CHR$(241)	"┴"	┴
CHR$(242)	"┬"	┬
CHR$(243)	"┤ "	┤
CHR$(244)	"│ "	│
CHR$(245)	"▌ "	▌
CHR$(246)	" ▐"	▐
CHR$(247)	"─"	─
CHR$(248)	"▬"	▬
CHR$(249)	"■"	■
CHR$(250)	"✓"	✓
CHR$(251)	"▪ "	▪
CHR$(252)	" ▪"	▪
CHR$(253)	"⌐ "	⌐
CHR$(254)	"▪ "	▪
CHR$(255)	"✗"	✗

C/?+G ASCII CONVERSION CHART (CONT)

SECONDARY ADDRESSES 7 OR 8
NORMAL PRINT MODE UPPER/LOWER CASE

CHR$ VALUE RECIEVED BY THE C/?+G INTERFACE	CHR$ VALUE, CHARACTER OR FUNCTION SENT	
	QUOTE MODE	NORMAL MODE
CHR$(0)	" "	CHR$(0)
CHR$(1)	"{$1}"	CHR$(1)
CHR$(2)	"{$2}"	CHR$(2)
CHR$(3)	"{$3}"	CHR$(3)
CHR$(4)	"{$4}"	CHR$(4)
CHR$(5)	"{WHT}"	CHR$(5)
CHR$(6)	"{$6}"	CHR$(6)
CHR$(7)	"{$7}"	CHR$(7)
CHR$(8)	"{DISH}"	START HI-RES GRAPHICS
CHR$(9)	"{ENSH}"	CHR$(9)
CHR$(10)		CHR$(10)
CHR$(11)	"{$11}"	CHR$(11)
CHR$(12)	"{$12}"	CHR$(12)
CHR$(13)		CHR$(13) OR CHR$(13) + CHR$(10)
CHR$(14)	"{SWLC}"	START EXPANDED PRINT
CHR$(15)	"{$15}"	END EXPANDED PRINT OR END GRAPHICS PRINT
CHR$(16)	"{$16}"	TAB FUNCTION
CHR$(17)	"{C/DN}"	START UPPER/LOWER CASE PRINT MODE
CHR$(18)	"{RVON}"	START REVERSED CHARACTERS
CHR$(19)	"{HOME}"	CHR$(19)
CHR$(20)	"{DEL}"	CHR$(20) OR CHR$(15) ON EPSON/STAR PRINTERS
CHR$(21)	"{$21}"	CHR$(21)
CHR$(22)	"{$22}"	CHR$(22)
CHR$(23)	"{$23}"	CHR$(23)
CHR$(24)	"{$24}"	CHR$(24)
CHR$(25)	"{$25}"	CHR$(25)

C/?+G ASCII CONVERSION CHART (CONT)

SECONDARY ADDRESSES 7 OR 8
NORMAL PRINT MODE UPPER/LOWER CASE

CHR$ VALUE RECIEVED BY THE C/?+G INTERFACE	CHR$ VALUE, CHARACTER OR FUNCTION SENT QUOTE MODE	 NORMAL MODE
CHR$(26)	"{$26}"	CHR$(26) – EXCEPT WHEN IN THE CHR$(8) GRAPHICS THEN IT MEANS REPEAT GRAPHICS CHARACTER
CHR$(27)	"{$27}"	CHR$(27) – UNLESS FOLOWED BY CHR$(16) THEN HI-RES TAB FUNCTION IS SENT
CHR$(28)	"{RED}"	CHR$(28)
CHR$(29)	"{C/RT}"	CHR$(29)
CHR$(30)	"{GRN}"	CHR$(30)
CHR$(31)	"{BLUE}"	CHR$(31)
CHR$(32)	" "	(SPACE)
CHR$(33)	"!"	!
CHR$(34)	"""	"
CHR$(35)	"#"	#
CHR$(36)	"$"	$
CHR$(37)	"%"	%
CHR$(38)	"&"	&
CHR$(39)	"'"	'
CHR$(40)	"("	(
CHR$(41)	")"	)
CHR$(42)	"*"	*
CHR$(43)	"+"	+
CHR$(44)	","	,
CHR$(45)	"-"	-
CHR$(46)	"."	.
CHR$(47)	"/"	/
CHR$(48)	"0"	0
CHR$(49)	"1"	1

C/?+G ASCII CONVERSION CHART (CONT)

SECONDARY ADDRESSES 7 OR 8
NORMAL PRINT MODE UPPER/LOWER CASE

CHR$ VALUE RECIEVED BY THE C/?+G INTERFACE	CHR$ VALUE, CHARACTER OR FUNCTION SENT	
	QUOTE MODE	NORMAL MODE
CHR$(50)	"2"	2
CHR$(51)	"3"	3
CHR$(52)	"4"	4
CHR$(53)	"5"	5
CHR$(54)	"6"	6
CHR$(55)	"7"	7
CHR$(56)	"8"	8
CHR$(57)	"9"	9
CHR$(58)	":"	:
CHR$(59)	";"	;
CHR$(60)	"<"	<
CHR$(61)	"="	=
CHR$(62)	">"	>
CHR$(63)	"?"	?
CHR$(64)	"@"	@
CHR$(65)	"a"	a
CHR$(66)	"b"	b
CHR$(67)	"c"	c
CHR$(68)	"d"	d
CHR$(69)	"e"	e
CHR$(70)	"f"	f
CHR$(71)	"g"	g
CHR$(72)	"h"	h
CHR$(73)	"i"	i
CHR$(74)	"j"	j
CHR$(75)	"k"	k
CHR$(76)	"l"	l
CHR$(77)	"m"	m
CHR$(78)	"n"	n

C/?+G ASCII CONVERSION CHART (CONT)

SECONDARY ADDRESSES 7 OR 8
NORMAL PRINT MODE UPPER/LOWER CASE

CHR$ VALUE RECIEVED BY THE C/?+G INTERFACE	CHR$ VALUE, CHARACTER OR FUNCTION SENT	
	QUOTE MODE	NORMAL MODE
CHR$(79)	"o"	o
CHR$(80)	"p"	p
CHR$(81)	"q"	q
CHR$(82)	"r"	r
CHR$(83)	"s"	s
CHR$(84)	"t"	t
CHR$(85)	"u"	u
CHR$(86)	"v"	v
CHR$(87)	"w"	w
CHR$(88)	"x"	x
CHR$(89)	"y"	y
CHR$(90)	"z"	z
CHR$(91)	"["	[
CHR$(92)	"£"	£
CHR$(93)	"]"	]
CHR$(94)	"↑"	↑
CHR$(95)	"←"	←
CHR$(96)	"—"	—
CHR$(97)	"A"	A
CHR$(98)	"B"	B
CHR$(99)	"C"	C
CHR$(100)	"D"	D
CHR$(101)	"E"	E
CHR$(102)	"F"	F
CHR$(103)	"G"	G
CHR$(104)	"H"	H
CHR$(105)	"I"	I
CHR$(106)	"J"	J
CHR$(107)	"K"	K

C/?+G ASCII CONVERSION CHART (CONT)

SECONDARY ADDRESSES 7 OR 8
NORMAL PRINT MODE UPPER/LOWER CASE

CHR$ VALUE RECIEVED BY THE C/?+G INTERFACE	CHR$ VALUE, CHARACTER OR FUNCTION SENT	
	QUOTE MODE	NORMAL MODE
CHR$(108)	"L"	L
CHR$(109)	"M"	M
CHR$(110)	"N"	N
CHR$(111)	"O"	O
CHR$(112)	"P"	P
CHR$(113)	"Q"	Q
CHR$(114)	"R"	R
CHR$(115)	"S"	S
CHR$(116)	"T"	T
CHR$(117)	"U"	U
CHR$(118)	"V"	V
CHR$(119)	"W"	W
CHR$(120)	"X"	X
CHR$(121)	"Y"	Y
CHR$(122)	"Z"	Z
CHR$(123)	"+"	+
CHR$(124)	"▒ "	▒
CHR$(125)	" I "	I
CHR$(126)	"✖"	✖
CHR$(127)	"▓"	▓
CHR$(128)	"{$128}"	CHR$(128)
CHR$(129)	"{ORNG}"	CHR$(129)
CHR$(130)	"{$130}"	CHR$(130)
CHR$(131)	"{$131}"	CHR$(131)
CHR$(132)	"{$132}"	CHR$(132)
CHR$(133)	"{F1}"	CHR$(133)
CHR$(134)	"{F3}"	CHR$(134)
CHR$(135)	"{F5}"	CHR$(135)
CHR$(136)	"{F7}"	CHR$(136)

C/?+G ASCII CONVERSION CHART (CONT)

SECONDARY ADDRESSES 7 OR 8
NORMAL PRINT MODE UPPER/LOWER CASE

CHR$ VALUE RECIEVED BY THE C/?+G INTERFACE	CHR$ VALUE, CHARACTER OR FUNCTION SENT QUOTE MODE	NORMAL MODE
CHR$(137)	"{F2}"	CHR$(137)
CHR$(138)	"{F4}"	CHR$(138)
CHR$(139)	"{F6}"	CHR$(139)
CHR$(140)	"{F8}"	CHR$(140)
CHR$(141)	"{SHRT}"	CHR$(141)
CHR$(142)	"{SWUC}"	CHR$(142)
CHR$(143)	"{$143}"	CHR$(143)
CHR$(144)	"{BLK}"	CHR$(144)
CHR$(145)	"{C/UP}"	START UPPER CASE/ GRAPHICS MODE
CHR$(146)	"{RVOF}"	END REVERSED CHARACTERS
CHR$(147)	"{CLR}"	CHR$(147)
CHR$(148)	"{INS}"	CHR$(148)
CHR$(149)	"{BRN}"	CHR$(149)
CHR$(150)	"{LRED}"	CHR$(150)
CHR$(151)	"{GRY1}"	CHR$(151)
CHR$(152)	"{GRY2}"	CHR$(152)
CHR$(153)	"{LGRN}"	CHR$(153)
CHR$(154)	"{LBLU}"	CHR$(154)
CHR$(155)	"{GRY3}"	CHR$(155)
CHR$(156)	"{PURP}"	CHR$(156)
CHR$(157)	"{C/LF}"	CHR$(157)
CHR$(158)	"{YELO}"	CHR$(158)
CHR$(159)	"{CYAN}"	CHR$(159)
CHR$(160)	" "	(SPACE)
CHR$(161)	"▌"	▌
CHR$(162)	"▄"	▄
CHR$(163)	"▀"	▀
CHR$(164)	"_"	_
CHR$(165)	"l "	l

C/?+G ASCII CONVERSION CHART (CONT)

SECONDARY ADDRESSES 7 OR 8
NORMAL PRINT MODE UPPER/LOWER CASE

CHR$ VALUE RECIEVED BY THE C/?+G INTERFACE	CHR$ VALUE, CHARACTER OR FUNCTION SENT	
	QUOTE MODE	NORMAL MODE
CHR$(166)	"▓"	▓
CHR$(167)	" ⎮"	⎮
CHR$(168)	"⠃"	⠃
CHR$(169)	"▓"	▓
CHR$(170)	" ▐"	▐
CHR$(171)	" ├"	├
CHR$(172)	" ■"	■
CHR$(173)	" ∟"	∟
CHR$(174)	"┐ "	┐
CHR$(175)	"▁"	▁
CHR$(176)	" ┌"	┌
CHR$(177)	"⊥"	⊥
CHR$(178)	"┬"	┬
CHR$(179)	"┤ "	┤
CHR$(180)	"⎮ "	⎮
CHR$(181)	"▌ "	▌
CHR$(182)	" ▐"	▐
CHR$(183)	"▬"	▬
CHR$(184)	"▬"	▬
CHR$(185)	"▄"	▄
CHR$(186)	"✓"	✓
CHR$(187)	"▪ "	▪
CHR$(188)	" ▪"	▪
CHR$(189)	" ⌙ "	⌙
CHR$(190)	" ▪ "	▪
CHR$(191)	"▙"	▙
CHR$(192)	"▁"	▁
CHR$(193)	"A"	A
CHR$(194)	"B"	B
CHR$(195)	"C"	C

C/?+G ASCII CONVERSION CHART (CONT)

SECONDARY ADDRESSES 7 OR 8
NORMAL PRINT MODE UPPER/LOWER CASE

CHR$ VALUE RECIEVED BY THE C/?+G INTERFACE	CHR$ VALUE, CHARACTER OR FUNCTION SENT	
	QUOTE MODE	NORMAL MODE
CHR$(196)	"D"	D
CHR$(197)	"E"	E
CHR$(198)	"F"	F
CHR$(199)	"G"	G
CHR$(200)	"H"	H
CHR$(201)	"I"	I
CHR$(202)	"J"	J
CHR$(203)	"K"	K
CHR$(204)	"L"	L
CHR$(205)	"M"	M
CHR$(206)	"N"	N
CHR$(207)	"O"	O
CHR$(208)	"P"	P
CHR$(209)	"Q"	Q
CHR$(210)	"R"	R
CHR$(211)	"S"	S
CHR$(212)	"T"	T
CHR$(213)	"U"	U
CHR$(214)	"V"	V
CHR$(215)	"W"	W
CHR$(216)	"X"	X
CHR$(217)	"Y"	Y
CHR$(218)	"Z"	Z
CHR$(219)	"+"	+
CHR$(220)	"▓ "	▓
CHR$(221)	" I "	I
CHR$(222)	"✕"	✕
CHR$(223)	"▓▓"	▓▓
CHR$(224)	" "	
CHR$(225)	"▌ "	▌

C/?+G ASCII CONVERSION CHART (CONT)

SECONDARY ADDRESSES 7 OR 8
NORMAL PRINT MODE UPPER/LOWER CASE

CHR$ VALUE RECIEVED BY THE C/?+G INTERFACE	CHR$ VALUE, CHARACTER OR FUNCTION SENT	
	QUOTE MODE	NORMAL MODE
CHR$(226)	"▄"	▄
CHR$(227)	"▬"	▬
CHR$(228)	"_"	_
CHR$(229)	"│ "	│
CHR$(230)	"▓"	▓
CHR$(231)	" │"	│
CHR$(232)	"↔"	↔
CHR$(233)	"▓"	▓
CHR$(234)	" ▌"	▌
CHR$(235)	" ├"	├
CHR$(236)	" ■"	■
CHR$(237)	" └"	└
CHR$(238)	"┐ "	┐
CHR$(239)	"▃"	▃
CHR$(240)	" ┌"	┌
CHR$(241)	"┴"	┴
CHR$(242)	"┬"	┬
CHR$(243)	"┤ "	┤
CHR$(244)	"▌ "	▌
CHR$(245)	"▌ "	▌
CHR$(246)	" ▐"	▐
CHR$(247)	"▬"	▬
CHR$(248)	"▬"	▬
CHR$(249)	"▄"	▄
CHR$(250)	"✓"	✓
CHR$(251)	"▪ "	▪
CHR$(252)	" ▬"	▬
CHR$(253)	"↵ "	↵
CHR$(254)	"▪ "	▪
CHR$(255)	"✗"	✗

CARD/PRINT +G — APPENDIX TO MANUAL
CARDCO, Inc. — (316) 267-6525

INDEX TO C/?+G MANUAL
****

INDEX TO C/?+G MANUAL
****

INDEX TO C/?+G MANUAL
****

CARD/PRINT +G — APPENDIX TO MANUAL
CARDCO, Inc.   —   (316) 267-6525

INDEX TO C/?+G MANUAL
****

VIC-20 & C-64 are registered Trademarks of Commodore, International